

Approved by:
Checked by:
Issued by:

# **SPECIFICATION**


PRODUCT: SAW RESONATOR

MODEL: HR433.42B QCC4A

HOPE MICROELECTRONICS CO.,LIMITED

The HR433.42B is a true one-port, surface-acoustic-wave (**SAW**) resonator in a surface-mount ceramic **QCC4A** case. It provides reliable, fundamental-mode, quartz frequency stabilization i.e. in transmitters or local oscillators operating at **433.420** MHz.

## 1.Package Dimension (QCC4A)



Pin	Configuration			
1	Input / Output			
3	Output / Input			
2/4	Case Ground			


Sign	Data (unit: mm) Sig		Data (unit: mm)
Α	1.2	D	1.4
В	0.8	Е	5.0
С	0.5	F	3.5

## 2.Marking

HR433.42B


Laser Marking

## 3. Equivalent LC Model and Test Circuit




## **4.Typical Application Circuits**


1) Low-Power Transmitter Application




## 2) Local Oscillator Application



#### 5. Typical Frequency Response



## **6.Temperature Characteristics**



The curve shown above accounts for resonator contribution only and does not include oscillator temperature characteristics.

#### 7.Performance

## 7-1.Maximum Ratings

Rating		Value	Unit
CW RF Power Dissipation	Р	0	dBm
DC Voltage Between Terminals	$V_{DC}$	± 30	V
Storage Temperature Range	$T_{ m stg}$	-40 to +85	
Operating Temperature Range	$T_{A}$	-10 to +60	

#### 7-2. Electronic Characteristics

	Characteristic	Sym	Minimum	Typical	Maximum	Unit
Center Frequency (+25 )	Absolute Frequency	f <sub>C</sub>	433.345		433.495	MHz
	Tolerance from 433.420 MHz	$\Delta f_{C}$		± 75		kHz
Insertion Loss		IL		1.3	1.8	dB
Quality Factor	Unloaded Q	Q <sub>U</sub>		9,425		
	50 Ω Loaded Q	$Q_L$		1,300		
Temperature Stability	Turnover Temperature	T <sub>0</sub>	25		55	
	Turnover Frequency	$f_0$		f <sub>C</sub>		kHz
	Frequency Temperature Coefficient	FTC		0.032		ppm/ <sup>2</sup>
Frequency Aging Absolute Value during the First Year		fA		10		ppm/yr
DC Insulation Resistance Between Any Two Terminals			1.0			ΜΩ
RF Equivalent RLC Model	Motional Resistance	R <sub>M</sub>		16	23	Ω
	Motional Inductance	L <sub>M</sub>		55.4029		μН
	Motional Capacitance	См		2.4363		fF
	Shunt Static Capacitance	C <sub>0</sub>	2.20	2.45	2.70	pF

(i) CAUTION: Electrostatic Sensitive Device. Observe precautions for handling!

### C 2003. All Rights Reserved.

- The center frequency, f<sub>C</sub>, is measured at the minimum IL point with the resonator in the 50 test system.
- Unless noted otherwise, case temperature T<sub>C</sub> = +25°C±2°C.
- 3. Frequency aging is the change in f<sub>C</sub> with time and is specified at +65°C or less. Aging may exceed the specification for prolonged temperatures above +65°C. Typically, aging is greatest the first year after manufacture, decreasing in subsequent years.
- 4. Turnover temperature,  $T_0$ , is the temperature of maximum (or turnover) frequency,  $f_0$ . The nominal frequency at any case temperature,  $T_C$ , may be calculated from:  $f = f_0 [1 FTC (T_0 T_C)^2]$ .
- 5. This equivalent RLC model approximates resonator performance near the resonant frequency and is provided for reference only. The capacitance C<sub>0</sub> is the measured static (nonmotional) capacitance between the two terminals. The measurement includes case parasitic capacitance.
- Derived mathematically from one or more of the following directly measured parameters: f<sub>C</sub>, IL, 3 dB bandwidth, f<sub>C</sub> versus T<sub>C</sub>, and C<sub>0</sub>.
- The specifications of this device are based on the test circuit shown above and subject to change or obsolescence without notice.
- 8. Typically, equipment utilizing this device requires emissions testing and government approval, which is the responsibility of the equipment manufacturer.
- 9. Our liability is only assumed for the Surface Acoustic Wave (SAW) component(s) per se, not for applications, processes and circuits implemented within components or assemblies.
- 10. For questions on technology, prices and delivery, please contact our sales offices or e-mail sales@hoperf.com.