



BAT40V

SURFACE MOUNT SCHOTTKY BARRIER DIODE ARRAYS

Features


- Low Forward Voltage Drop
- Fast Switching
- Ultra-Small Surface Mount Package
- PN Junction Guard Ring for Transient and ESD Protection
- Lead Free by Design/RoHS Compliant (Note 1)
- Qualified to AEC-Q101 Standards for High Reliability
- "Green" Device (Notes 4 and 5)

Mechanical Data

- Case: SOT-563, Molded Plastic
- Case Material: Molded Plastic. UL Flammability Classification Rating 94V-0
- Moisture Sensitivity: Level 1 per J-STD-020D
- Terminal Connections: See Diagram
- Terminals: Finish Matte Tin annealed over Alloy 42 leadframe. Solderable per MIL-STD-202, Method 208
- Terminals: Lead Bearing Terminal Plating available.
- Marking Information: See Page 2
- Ordering Information: See Page 2
- Weight: 0.003 grams (approximate)







Top View

Bottom View

Device Schematic

Maximum Ratings @T_A = 25°C unless otherwise specified

Characte	ristic		Symbol	Value	Unit
Peak Repetitive Reverse Voltage Working Peak Reverse Voltage DC Blocking Voltage			V _{RRM} V _{RWM} V _R	40	V
Forward Continuous Current		(Note 2)	l _F	200	mA
Repetitive Peak Forward Current		(Note 2)	I _{FRM}	350	mA
Forward Surge Current	(Note 2)	@ tp =10ms	I _{FSM}	750	mA

Thermal Characteristics

Characteristic	Symbol	Value	Unit
Power Dissipation (Note 2)	P _D	150	mW
Thermal Resistance, Junction to Ambient Air (Note 2)	$R_{ heta JA}$	833	°C/W
Operating and Storage Temperature Range	T _J , T _{STG}	-65 to +125	°C


Electrical Characteristics @T_A = 25°C unless otherwise specified


Characteristic			Min	Тур	Max	Unit	Test Condition
Reverse Breakdown Voltage	(Note 3)	$V_{(BR)R}$	40		_	٧	$I_R = 100 \mu A$
Forward Voltage		V _F			330 420 800 1000	mV	I _F = 2.0mA I _F = 15mA I _F = 100mA I _F = 200mA
Reverse Leakage Current	(Note 3)	I_R	_	_	500	nA	$V_R = 25V$
Total Capacitance		C _T	_	_	10	pF	$V_R = 1.0V, f = 1.0MHz$
Reverse Recovery Time		t _{rr}	_	_	5.0	ns	$I_F = 10$ mA through $I_R = 10$ mA to $I_R = 1.0$ mA, $R_L = 100$ Ω


Notes:


- 1. No purposefully added lead.
- Device mounted on FR-4 PCB, 1 inch x 0.85 inch x 0.062 inch; pad layout as shown on Diodes Inc. suggested pad layout document AP02001, which can be found on our website at http://www.diodes.com/datasheets/ap02001.pdf. T_A = 25°C.
- Short duration pulse test used to minimize self-heating effect.
- 4. Diodes Inc.'s "Green" policy can be found on our website at http://www.diodes.com/products/lead_free/index.php.
- Product manufactured with Date Code UO (week 40, 2007) and newer are built with Green Molding Compound. Product manufactured prior to Date Code UO are built with Non-Green Molding Compound and may contain Halogens or Sb2O3 Fire Retardants.












Ordering Information (Note 6)

Part Number	Case	Packaging
BAT40V-7	SOT-563	3000/Tape & Reel

Notes: 6. For packaging details, go to our website at http://www.diodes.com/datasheets/ap02007.pdf.

Marking Information




KAX = Product Type Marking Code YM = Date Code Marking Y = Year (ex: R = 2004) M = Month (ex: 9 = September)


Date Code Kev

Year	2004	2005	2006	2007	2008	2009	2010	2011	2012	2013	2014	2015
Code	R	S	Т	J	V	W	Х	Υ	Z	Α	В	С
Month	Jan	Feb	Mar	Apr	May	Jun	Jul	Aug	Sep	Oct	Nov	Dec




Package Outline Dimensions





	SOT-563						
Dim	Min	Max	Тур				
Α	0.15	0.30	0.20				
В	1.10	1.25	1.20				
С	1.55	1.70	1.60				
D	-	-	0.50				
G	0.90	1.10	1.00				
Н	1.50	1.70	1.60				
K	0.55	0.60	0.60				
L	0.10	0.30	0.20				
М	0.10	0.18	0.11				
All	Dimens	ions in	mm				

Suggested Pad Layout



Dimensions	Value (in mm)
Z	2.2
G	1.2
Х	0.375
Υ	0.5
С	1.7
E	0.5

IMPORTANT NOTICE

Diodes Incorporated and its subsidiaries reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to any product herein. Diodes Incorporated does not assume any liability arising out of the application or use of any product described herein; neither does it convey any license under its patent rights, nor the rights of others. The user of products in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on our website, harmless against all damages.

LIFE SUPPORT

Diodes Incorporated products are not authorized for use as critical components in life support devices or systems without the expressed written approval of the President of Diodes Incorporated.