

9.50-10.50GHz 2-Watt Internally-Matched Power FET

FEATURES

- 9.50 -10.50GHz Bandwidth
- Input/Output Impedance Matched to 50 Ohms
- +33.5 dBm Output Power at 1dB Compression
- 8.0 dB Power Gain at 1dB Compression
- 30% Power Added Efficiency
- -46 dBc IM3 at Po = 22.5 dBm SCL
- 100% Tested for DC, RF, and R_{TH}



ELECTRICAL CHARACTERISTICS (T_a = 25°C)



Caution! ESD sensitive device.

SYMBOL	PARAMETERS/TEST CONDITIONS ¹	MIN	TYP	MAX	UNITS
P _{1dB}	Output Power at 1dB Compression f = 9.50-10.50GHz V _{DS} = 10 V, I _{DSQ} ≈ 550mA	32.5	33.5		dBm
G _{1dB}	Gain at 1dB Compression $f = 9.50-10.50GHz$ $V_{DS} = 10 \text{ V}, I_{DSQ} \approx 550\text{mA}$	7.0	8.0		dB
ΔG	Gain Flatness $f = 9.50-10.50GHz$ $V_{DS} = 10 \text{ V}, I_{DSQ} \approx 550\text{mA}$			±0.6	dB
PAE	Power Added Efficiency at 1dB Compression $V_{DS} = 10 \text{ V}, I_{DSQ} \approx 550 \text{mA}$ f = 9.50-10.50GHz		30		%
ld₁ _{dB}	Drain Current at 1dB Compression f = 9.50-10.50GHz		600	700	mA
IM3	Output 3rd Order Intermodulation Distortion $\Delta f = 10$ MHz 2-Tone Test; Pout = 22.5 dBm S.C.L ² $V_{DS} = 10$ V, $I_{DSQ} \approx 65\%$ IDSS $f = 10.50$ GHz	-43	-46		dBc
I _{DSS}	Saturated Drain Current $V_{DS} = 3 \text{ V}, V_{GS} = 0 \text{ V}$		1000	1250	mA
V _P	Pinch-off Voltage $V_{DS} = 3 \text{ V}, I_{DS} = 10 \text{ mA}$		-2.5	-4.0	V
R _{TH}	Thermal Resistance ³		11	12	°C/W

Note: 1. Tested with 100 Ohm gate resistor.

2. S.C.L. = Single Carrier Level.

3. Overall Rth depends on case mounting.

ABSOLUTE MAXIMUM RATING FOR EFE

SYMBOLS	PARAMETERS	ABSOLUTE ¹	CONTINUOUS ²	
Vds	Drain-Source Voltage	15V	10V	
Vgs	Gate-Source Voltage	-5V	-4V	
lgf	Forward Gate Current	24mA	7.2mA	
lgr	Reverse Gate Current	-4.8mA	-1.2mA	
Pin	Input Power	33.0dBm	@ 3dB Compression	
Tch	Channel Temperature	175C	175C	
Tstg	Storage Temperature	-65C to +175C	-65C to +175C	
Pt	Total Power Dissipation	12.5W	12.5W	

Note: 1. Exceeding any of the above ratings may result in permanent damage.

2. Exceeding any of the above ratings may reduce MTTF below design goals.


Phone: 408-737-1711 Fax: 408-737-1868 Web: www.excelics.com




9.50-10.50GHz 2-Watt Internally-Matched Power FET

PERFORMANCE DATA

Typical S-Parameters (T= 25°C, 50Ω system, de-embedded to edge of package) V_{DS} = 10 V, I_{DSQ} = 550mA







FREQ	S11		S21		S12		S22	
(GHz)	MAG	ANG	MAG	ANG	MAG	ANG	MAG	ANG
8.75	0.801	-144.750	1.666	55.890	0.045	10.590	0.698	-25.380
9.00	0.748	-164.560	1.962	36.560	0.059	-9.970	0.658	-39.760
9.25	0.650	171.690	2.305	14.740	0.076	-32.680	0.600	-57.400
9.50	0.522	141.280	2.669	-10.520	0.098	-58.510	0.516	-79.320
9.75	0.364	101.620	2.943	-38.640	0.117	-86.820	0.405	-107.410
10.00	0.229	42.070	3.009	-67.750	0.130	-115.840	0.288	-144.010
10.25	0.227	-31.690	2.929	-95.780	0.134	-143.460	0.223	167.180
10.50	0.309	-80.620	2.712	-122.110	0.132	-168.960	0.232	122.730
10.75	0.369	-111.080	2.470	-146.280	0.126	168.060	0.276	93.950
11.00	0.399	-134.340	2.254	-168.390	0.123	146.710	0.329	75.830
11.25	0.402	-154.030	2.085	170.040	0.117	126.180	0.377	62.360




9.50-10.50GHz 2-Watt Internally-Matched Power FET

Power De-rating Curve and IM3 Definition






Typical Power Data (V_{DS} = 10 V, I_{DSQ} = 550 mA)



Typical IM3 Data (V_{DS} = 10 V, I_{DSQ} ≈ 65% IDSS)






9.50-10.50GHz 2-Watt Internally-Matched Power FET

PACKAGES OUTLINE

Dimensions in inches, Tolerance ± .005 unless otherwise specified


EIC0910-2 (Hermetic)





Caution! ESD sensitive device.

EIC0910-2NH (Non-Hermetic)





Caution! ESD sensitive device.

ORDERING INFORMATION

Part Number	Packages	Grade ¹	f _{Test} (GHz)	P _{1dB} (min)	IM ₃ (min) ²
EIC0910-2	Hermetic	Industrial	9.50-10.50GHz	32.5	-43
EIC0910-2NH	Non-Hermetic	Industrial	9.50-10.50GHz	32.5	-43

Notes:

- 1. Contact factory for military and hi-rel grades.
- 2. Exact test conditions are specified in "Electrical Characteristics" table.

DISCLAIMER

EXCELICS SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. EXCELICS DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN.

LIFE SUPPORT POLICY

EXCELICS SEMICONDUCTOR PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF EXCELICS SEMICONDUCTOR, INC. AS HERE IN:

- 1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.
- 2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness