



NPT³ IGBT
in ISOPLUS247™

 $I_{C25} = 36 \text{ A}$
 $V_{CES} = 1200 \text{ V}$
 $V_{CE(sat)typ} = 2.4 \text{ V}$


| IGBT | | Maximum Ratings | |
|-----------------------|---|-----------------|---------------|
| Symbol | Conditions | | |
| V_{CES} | $T_{VJ} = 25^\circ\text{C to } 150^\circ\text{C}$ | 1200 | V |
| V_{GES} | | ± 20 | V |
| I_{C25} | $T_C = 25^\circ\text{C}$ | 29 | A |
| I_{C90} | $T_C = 90^\circ\text{C}$ | 19 | A |
| I_{CM} V_{CEK} | $V_{GE} = \pm 15 \text{ V}; R_G = 68 \Omega; T_{VJ} = 125^\circ\text{C}$ RBSOA Clamped inductive load; $L = 100 \mu\text{H}$ | 40 | A |
| | | V_{CES} | |
| t_{SC} (SCSOA) | $V_{CE} = 900 \text{ V}; V_{GE} = \pm 15 \text{ V}; R_G = 68 \Omega$ $T_{VJ} = 125^\circ\text{C}; \text{non-repetitive}$ | 10 | μs |
| P_{tot} | $T_C = 25^\circ\text{C}$ | 130 | W |

Features

- NPT³ IGBT
 - low saturation voltage
 - positive temperature coefficient for easy paralleling
 - fast switching
 - short tail current for optimized performance in resonant circuits
- HiPerFRED™ diode
 - fast reverse recovery
 - low operating forward voltage
 - low leakage current
- ISOPLUS247™ package
 - isolated back surface
 - low coupling capacity between pins and heatsink
 - high reliability
 - industry standard outline

| Symbol | Conditions | Characteristic Values | | | | |
|--|---|---|--|------|----------------------------------|------------|
| | | min. | typ. | max. | | |
| $V_{CE(sat)}$ | $I_C = 20 \text{ A}; V_{GE} = 15 \text{ V}; T_{VJ} = 25^\circ\text{C}$ $T_{VJ} = 125^\circ\text{C}$ | | 2.4 2.8 | 2.8 | V V | |
| $V_{GE(th)}$ | $I_C = 0.6 \text{ mA}; V_{GE} = V_{CE}$ | 4.5 | | 6.5 | V | |
| I_{CES} | $V_{CE} = V_{CES}; V_{GE} = 0 \text{ V}; T_{VJ} = 25^\circ\text{C}$ $T_{VJ} = 125^\circ\text{C}$ | | 0.2 | 0.2 | mA mA | |
| I_{GES} | $V_{CE} = 0 \text{ V}; V_{GE} = \pm 20 \text{ V}$ | | | 200 | nA | |
| $t_{d(on)}$ t_r $t_{d(off)}$ t_f E_{on} E_{off} | Inductive load $L = 100 \mu\text{H}; T_{VJ} = 125^\circ\text{C}$ $V_{CE} = 600 \text{ V}; I_C = 25 \text{ A}$ $V_{GE} = \pm 15 \text{ V}; R_G = 68 \Omega$ | | 205 105 320 175 4.1 1.5 | | ns ns ns ns mJ mJ | |
| C_{ies} | | $V_{CE} = 25 \text{ V}; V_{GE} = 0 \text{ V}; f = 1 \text{ MHz}$ | | 1.2 | | nF |
| Q_{Gon} | | $V_{CE} = 600 \text{ V}; V_{GE} = 15 \text{ V}; I_C = 20 \text{ A}$ | | 100 | | nC |
| R_{thJC} R_{thCH} | | with heatsink compound | | 0.5 | 0.96 | K/W K/W |

Applications

- single switches
- choppers with complementary free wheeling diodes
- phaselegs, H bridges, three phase bridges e.g. for
 - power supplies, UPS
 - AC, DC and SR drives
 - induction heating

Diode [D1 version only]

| Symbol | Conditions | Maximum Ratings | |
|-----------|--------------------------|-----------------|---|
| I_{F25} | $T_C = 25^\circ\text{C}$ | 25 | A |
| I_{F90} | $T_C = 90^\circ\text{C}$ | 15 | A |


| Symbol | Conditions | Characteristic Values | | | |
|------------|--|---|------|------|-----|
| | | min. | typ. | max. | |
| V_F | $I_F = 20\text{ A}; V_{GE} = 0\text{ V};$ | $T_{VJ} = 25^\circ\text{C}$ | 2.6 | 3.0 | V |
| | | $T_{VJ} = 125^\circ\text{C}$ | 2.0 | | V |
| I_{RM} | $V_R = 600\text{ V}; L = 100\ \mu\text{H}; T_{VJ} = 125^\circ\text{C}$ | | 16 | | A |
| t_{rr} | | $di_F/dt = -400\text{ A}/\mu\text{s}; I_F = 15\text{ A}; V_{GE} = 0\text{ V}$ | 130 | | ns |
| R_{thJC} | with heatsink compound | | 2.3 | | K/W |
| R_{thCH} | | | 1.3 | | |

Module

| Symbol | Conditions | Maximum Ratings | |
|------------|--|-----------------|------------------|
| T_{VJ} | | -55...+150 | $^\circ\text{C}$ |
| T_{stg} | | -55...+150 | $^\circ\text{C}$ |
| V_{ISOL} | $I_{ISOL} \leq 1\text{ mA}; 50/60\text{ Hz}$ | 2500 | V~ |
| F_C | mounting force with clip | 20...120 | N |

| Symbol | Conditions | Characteristic Values | | | |
|--------|---|-----------------------|------|------|----|
| | | min. | typ. | max. | |
| C_p | coupling capacity between shorted pins and mounting tab in the case | | 30 | | pF |
| Weight | | | 6 | | g |

ISOPLUS247™ Outline



| DIM. | MILLIMETER | | INCHES | |
|------|------------|-------|-----------|-------|
| | MIN | MAX | MIN | MAX |
| A | 4,83 | 5,21 | 0,190 | 0,205 |
| A1 | 2,29 | 2,54 | 0,090 | 0,100 |
| A2 | 1,91 | 2,16 | 0,075 | 0,085 |
| b | 1,14 | 1,40 | 0,045 | 0,055 |
| b1 | 1,91 | 2,15 | 0,075 | 0,085 |
| b2 | 2,92 | 3,20 | 0,115 | 0,126 |
| C | 0,61 | 0,83 | 0,024 | 0,033 |
| D | 20,80 | 21,34 | 0,819 | 0,840 |
| E | 15,75 | 16,13 | 0,620 | 0,635 |
| e | 5,45 BSC | | 0,215 BSC | |
| L | 19,81 | 20,60 | 0,780 | 0,811 |
| L1 | 3,81 | 4,38 | 0,150 | 0,172 |
| Q | 5,59 | 6,20 | 0,220 | 0,244 |
| R | 4,32 | 4,85 | 0,170 | 0,191 |
| S | 13,21 | 13,72 | 0,520 | 0,540 |
| T | 15,75 | 16,26 | 0,620 | 0,640 |
| U | 1,65 | 2,03 | 0,065 | 0,080 |
| W | - | 0,10 | - | 0,004 |

Die konvexe Form des Substrates ist typ. < 0.04 mm über der Kunststoffoberfläche der Bauteilunterseite
The convex bow of substrate is typ. < 0.04 mm over plastic surface level of device bottom side

Die Gehäuseabmessungen entsprechen dem Typ TO-247 AD gemäß JEDEC außer Schraubloch und L_{max} .
This drawing will meet all dimensions requirement of JEDEC outline TO-247 AD except screw hole and except L_{max} .




Fig. 1 Typ. output characteristics




Fig. 2 Typ. output characteristics




Fig. 3 Typ. transfer characteristics




Fig. 4 Typ. forward characteristics of free wheeling diode




Fig. 5 Typ. turn on gate charge




Fig. 6 Typ. turn off characteristics of free wheeling diode




Fig. 7 Typ. turn on energy and switching times versus collector current




Fig. 8 Typ. turn off energy and switching times versus collector current




Fig. 9 Typ. turn on energy vs gate resistor




Fig. 10 Typ. turn off energy and switching times versus gate resistor




Fig. 11 Reverse biased safe operating area RBSOA




Fig. 12 Typ. transient thermal impedance

Thermal Analysis Model

$$Z_{th}(t) = \sum_{i=1}^n \left[R_i \cdot \left(1 - \exp\left(-\frac{t}{\tau_i}\right) \right) \right]$$