


# SD1528-06

# **RF & MICROWAVE TRANSISTORS AVIONICS APPLICATIONS**

- DESIGNED FOR HIGH POWER PULSED IFF, DME, TACAN APPLICATIONS
- 20 W (typ.) IFF 1030 1090 MHz
- 15 W (min.) DME 1025 1150 MHz
- 15 W (typ.) TACAN 960 1215 MHz
- REFRACTORY GOLD METALLIZATION
- EMITTER BALLASTED AND LOW THERMAL RESISTANCE FOR RELIABILITY AND RUGGEDNESS
- 20:1 LOAD VSWR CAPABILITY @ SPECIFIED OPERATING CONDITIONS
- INPUT MATCHED, COMMON BASE CONFIGURATION



Ч

3. Emitter

4. Base

1. Collector

2. Base

#### DESCRIPTION

The SD1528-06 is a gold metallized epitaxial silicon NPN power transistor. The SD1528-06 is designed for applications requiring high peak power and low duty cycles such as IFF, DME and TACAN. The SD1528-06 is packaged in the .280" input matched stripline package, resulting in improved broadband performance and low thermal resistance.

#### **ABSOLUTE MAXIMUM RATINGS** ( $T_{case} = 25^{\circ}C$ )

Symbol	Parameter	Value	Unit	
V <sub>CBO</sub>	Collector-Base Voltage	r-Base Voltage 65		
V <sub>CES</sub>	Collector-Emitter Voltage	65	V	
V <sub>EBO</sub>	Emitter-Base Voltage	3.5	V	
lc	Device Current	1.5	А	
PDISS	Power Dissipation	87.5	W	
TJ	Junction Temperature	+200	°C	
T <sub>STG</sub>	Storage Temperature	– 65 to +150	°C	

#### THERMAL DATA

R <sub>TH(j-c)</sub>	Junction-Case Thermal Resistance	2.0	°C/W	
November 1992				

# SD1528-06

## **ELECTRICAL SPECIFICATIONS** $(T_{case} = 25^{\circ}C)$

#### STATIC

Symbol	Test Conditions	Value			Unit		
Symbol	Symbol Test Conditions		Min.	Тур.	Max.	Unit	
ВVсво	$I_C = 10 mA$	$I_E = 0 m A$		65	_	—	V
BVCES	$I_{C} = 25 \text{mA}$	$V_{BE} = 0V$		65	_	—	V
BVEBO	$I_E = 1mA$	$I_C = 0 m A$		3.5	_	_	V
ICES	$V_{CE} = 50V$	$I_E = 0 m A$				2	mA
hFE	$V_{CE} = 5V$	$I_C = .1A$		10		200	


#### DYNAMIC

Symbol Test Conditions			Value			Unit
Symbol	Test conditions		Min.	Тур.	Max.	om
Pout	$f = 1025 - 1150 MHz P_{IN} = 1.5 W V_{CE} = 50 V$		15	—		W
GP	$f = 1025 - 1150 MHz P_{IN} = 1.5 W V_{CE} = 50 V$		10	—	_	dB
η <sub>c</sub>	$f = 1025 - 1150 MHz P_{IN} = 1.5 W V_{CE} = 50 V$		30	_		%


Note: Pulse Width =  $10\mu$ sec, Duty Cycle = 1%

# **TYPICAL PERFORMANCE**

#### POWER OUTPUT vs POWER INPUT




#### **POWER OUTPUT vs FREQUENCY**





## IMPEDANCE DATA

TYPICAL INPUT IMPEDANCE




TYPICAL COLLECTOR LOAD IMPEDANCE

	<b>—</b> ( )	<b>—</b> ( )
FREQ.	Z <sub>IN</sub> (Ω)	$Z_{CL}(\Omega)$
960 MHz	2.5 + j 12.5	17.0 + j 15.5
1030 MHz	3.5 + j 12.5	17.0 + j 14.5
1090 MHz	3.0 + j 13.5	19.5 + j 12.5
1150 MHz	3.5 + j 14.0	18.0 + j 12.0
1215 MHz	5.0 + j 17.0	16.0 + j 12.0



# PACKAGE MECHANICAL DATA



Information furnished is believed to be accurate and reliable. However, SGS-THOMSON Microelectronics assumes no responsability for the consequences of use of such information nor for any infringement of patents or other rights of third parties which may results from its use. No license is granted by implication or otherwise under any patent or patent rights of SGS-THOMSON Microelectronics. Specifications mentioned in this publication are subject to change without notice. This publication supersedes and replaces all information previously supplied. SGS-THOMSON Microelectronics products are not authorized for use as critical components in life support devices or systems without express written approval of SGS-THOMSON Microelectonics.

© 1994 SGS-THOMSON Microelectronics - All Rights Reserved

SGS-THOMSON Microelectronics GROUP OF COMPANIES Australia - Brazil - France - Germany - Hong Kong - Italy - Japan - Korea - Malaysia - Malta - Morocco - The Netherlands -Singapore - Spain - Sweden - Switzerland - Taiwan - Thailand - United Kingdom - U.S.A

