




## POWER TRANSISTORS

Switching transistors for horizontal deflection and television switch-mode power supply

Type	V <sub>CB0</sub> (V)	V <sub>CEO</sub> (V)	I <sub>c</sub> (A)	P <sub>tot</sub> (W)	V <sub>CEsat</sub> (V)	t <sub>f</sub> at I <sub>c</sub> (μs)	I <sub>c</sub> (A)	Case JEDEC
BU 126	750	300	3.0	40	<5.0	<0.7	4.0	TO-3
BU 204	1300	600	2.5	10	<5.0	<1.0	2.0	
BU 205	1500	700	2.5	10	<5.0	<1.0	2.0	
BU 206	1700	800	2.5	10	<5.0	<1.0	2.0	
BU207	1300	600	5.0	12.5	<5.0	<1.0	4.5	
BU 208	1500	700	5.0	12.5	<5.0	<1.0	4.5	
BU 208 A	1500	700	5.0	12.5	<1.0	<1.0	4.5	
BU 208 D	1500	700	5.0	12.5	<1.0	<1.0	4.5	
BU 326	800	325	6.0	75	<3.0	<1.0	4.0	
BU 326 A	900	400	6.0	75	<3.0	<1.0	4.0	
BU 526	900	400	8.0	86	<5.0	<1.0	8.0	
BU 536	1100	480	8.0	62	<5.0	<1.0	4.0	
BU 406	400	200	7.0	60	<1.0	<0.5	5.0	
BU 407	330	150	7.0	60	<1.0	<0.5	5.0	
BU 407D	330	150	7.0	60	<1.0	<0.5	5.0	
BU 505	1500	700	2.5	75	<5.0	<1.0	2.0	
BU 506	1500	700	4.0	78	<5.0	<1.0	3.0	
BU 426	800	375	6.0	70	<1.5	<0.75	2.5	
BU 426A	900	400	6.0	70	<1.5	<0.75		
BU 508	1500	700	8.0	125	<5.0	<1.0	4.5	
BU 508A	1500	700	8.0	125	<1.0	<1.0	4.5	
BU 508D	1500	700	8.0	125	<1.0	<1.0	4.5	
BU 705	1500	700	2.5	75	<5.0	<1.0	2.0	
BU 903	1350	550	8.0	125	<2.0	<1.0	3.2	
BU 908	1500	700	8.0	125	<2.0	<1.0	3.2	
BUV 70	1300	600	10	140	<2.0	<0.6	5.0	
BUV 71	1500	800	10	140	<3.0	<0.7	5.0	