

### POWER RELAY

# 1 POLE—16 A (HEAVY POWER CONTROL) **VSB SERIES**

**RoHS** compliant

#### ■ FEATURES

- All or nothing relay
- UL, CSA, VDE, SEV, FIMKO, SEMKO, ÖVE, BSI recognized
- · Working class: C
- Type of service: continuous duty
- Heavy duty 16 A miniature power relay
- UL Class B (130°C) insulation
- · High isolation in small package
  - -Insulation distance: 8 mm
  - -Dielectric strength: 5,000 VAC (between coil and contacts)
  - —Surge strength: 10,000 V
- · Low power consumption and high sensitivity type available VSB-S)
- Plastic sealed (with tape) type available
- RoHS compliant since date code:0523 Please see page 6 for more information





#### ORDERING INFORMATION

<ul> <li>Plastic sealed (with tape) type available</li> <li>RoHS compliant since date code:0523         Please see page 6 for more information     </li> </ul>					
<b>O</b>	■ ORDERING INFORMATION				
VSB - 12 S T B [Example] _(a)_ (*) (b)_ (c)_ (d)_ (e)					
(a)	Series Name	VSB: VSB Series			
(b)	Nominal Voltage	Refer to the COIL DATA CHART			
(c)	Coil Type	Nil : Standard type (700 to 750 mW) S : High sensitivity type (530 mW)			
(d)	Contact Arrangement	M : 1 form A (SPST-NO) T : 1 form C (SPDT)			
(e)	Enclosure	B : Flux free type C : Plastic sealed type (with tape)			

Note: Actual marking omits the hyphen (-) of (\*)

#### **COIL DATA CHART**

MODEL		Nominal voltage	Coil resistance (±10%)	Must operate voltage*	Must release voltage*	Nominal power
Standard Type	VSB- 3()()	3 VDC	12.5 Ω	2.1 VDC	0.3 VDC	720 mW
	VSB- 5()()	5 VDC	36 Ω	3.5 VDC	0.5 VDC	700 mW
	VSB- 6()()	6 VDC	50 Ω	4.2 VDC	0.6 VDC	720 mW
	VSB- 9()()	9 VDC	115 Ω	6.3 VDC	0.9 VDC	700 mW
	VSB- 12()()	12 VDC	200 Ω	8.4 VDC	1.2 VDC	720 mW
	VSB- 14()()	14 VDC	280 Ω	9.8 VDC	1.4 VDC	700 mW
	VSB- 18()()	18 VDC	460 Ω	12.6 VDC	1.8 VDC	700 mW
	VSB- 24()()	24 VDC	820 Ω	16.8 VDC	2.4 VDC	700 mW
	VSB- 36()()	36 VDC	1,850 Ω	25.2 VDC	3.6 VDC	700 mW
	VSB- 48()()	48 VDC	3,300 Ω	33.6 VDC	4.8 VDC	700 mW
	VSB- 60()()	60 VDC	5,100 Ω	42.0 VDC	6.0 VDC	700 mW
	VSB-100 ( ) ( )	100 VDC	13,400 Ω	70.0 VDC	10.0 VDC	750 mW
	VSB- 3S()()	3 VDC	17 Ω	2.1 VDC	0.3 VDC	530 mW
	VSB- 5S()()	5 VDC	47 Ω	3.5 VDC	0.5 VDC	530 mW
	VSB- 6S()()	6 VDC	68 Ω	4.2 VDC	0.6 VDC	530 mW
l e	VSB- 9S()()	9 VDC	155 Ω	6.3 VDC	0.9 VDC	530 mW
T <sub>Y</sub>	VSB- 12S()()	12 VDC	270 Ω	8.4 VDC	1.2 VDC	530 mW
tivit	VSB- 14S()()	14 VDC	370 Ω	9.8 VDC	1.4 VDC	530 mW
High Sensitivity Type	VSB- 18S()()	18 VDC	610 Ω	12.6 VDC	1.8 VDC	530 mW
	VSB- 24S()()	24 VDC	1,100 Ω	16.8 VDC	2.4 VDC	530 mW
	VSB- 36S()()	36 VDC	2,450 Ω	25.2 VDC	3.6 VDC	530 mW
	VSB- 48S()()	48 VDC	4,400 Ω	33.6 VDC	4.8 VDC	530 mW
	VSB- 60S()()	60 VDC	6,800 Ω	42.0 VDC	6.0 VDC	530 mW
	VSB-100S()()	100 VDC	18,560 Ω	70.0 VDC	10.0 VDC	530 mW

Note: All values in the table are measured at 20°C. \*: Specified values are subject to pulse wave voltage

#### **SPECIFICATIONS**

Item			Standard Type VSB-()	High Sensitive type VSB-( )-S		
Contact	Arrangement		1 form A (SPST- NO) or 1 f	1 form A (SPST- NO) or 1 form C (SPDT)		
	Material		Silver alloy (AgSnO)	Silver alloy (AgSnO)		
	Configuration		Single	Single		
	Resistance (initial)		Maximum 100 mΩ at 1 A,	Maximum 100 mΩ at 1 A, 6 VDC		
	Rating		16 A, 250 VAC / 30 VDC	16 A, 250 VAC / 30 VDC		
	Maximum Carrying Current*1		16 A	16 A		
	Maximum Switching Rating		4,000 VA / 480W	4,000 VA / 480W		
	Maximum Switching Voltage		250 VAC / 150VDC	250 VAC / 150VDC		
	Maximum Switching Current		16A	16A		
	Maximum Switching Load*2		100 mA 5 VDC	100 mA 5 VDC		
Coil	Nominal Power (at 20°C)		700 to 750 mW	530 mW		
	Operate Power (at 20°C)		350 to 370 mW	260 mW		
	Operating Temperature		-40°C to +65°C (no frost)	-40°C to +75°C (no frost)		
Time	Operate (at nominal voltage)		Maximum 15ms	Maximum 15ms		
Value	Release (at nominal voltage)		Maximum 10ms	Maximum 10ms		
Life	Mechanical		2 x 10 <sup>7</sup> operations minimu	2 x 10 <sup>7</sup> operations minimum		
	Electrical		1 x 10 <sup>5</sup> operations minimu	1 x 10 <sup>5</sup> operations minimum (contact rating)		
Other	Vibration Resistance	Misoperation	10 to 55 Hz, at double amp	10 to 55 Hz, at double amplitude of 1.5 mm		
		Endurance	10 to 55Hz, at double amp	10 to 55Hz, at double amplitude of 1.5 mm		
	Shock Resistance	Misoperation	Min. 100m/s <sup>2</sup> (11±1ms)	Min. 100m/s <sup>2</sup> (11±1ms)		
		Endurance	Min. 1,000m/s <sup>2</sup> (6±1ms)	Min. 1,000m/s <sup>2</sup> (6±1ms)		
	Weight		Approximately 18g	Approximately 18g		

#### **■ INSULATION**


Item		VSB	Note	
Resistance (initial)		Minimum 1,000 MΩ	at 500 VDC	
Dielectric	open contacts	1,000 VAC (50/60 Hz) 1 min.		
Strength	coil and contacts	5,000 VAC (50/60 Hz) 1 min.		
Surge Voltage (coil and contact)		10,000 V	1.2 x 50µs standard wave	


#### ■ SAFETY STANDARDS


Туре	Compliance	Contact rating
UL	UL 508, 873	Flammability: UL 94-V0 (plastics)
	E56140	16A, 250VAC/30VDC (resistive) 1/3 HP, 250VAC/125VAC
CSA	C22.2 No. 14 LR 35579	Pilot duty: C150
VDE	0435, 0631, 0700, 0860	


Need to consider the head from PCB when max. current is more than 10A.
 Minimum switching loads mentioned above are reference values. Please perform the confirmation test with the actual load before production since reference values may vary according to switching frequencies, environmental conditions and expected reliability levels.


#### CHARACTERISTIC DATA













#### REFERENCE DATA



Distribution of Operate & Release Voltage

Release




20

Operation (×10<sup>3</sup>)

100

Initial




Operation (×10<sup>3</sup>)

#### **■** DIMENSIONS


#### Dimensions


VSB-M type




 PC board mounting hole layout (BOTTOM VIEW)


Schematics (BOTTOM VIEW)







VSB type










VSB-MC type (Plastic sealed type with tape)









VSB-C type (Plastic sealed type with tape)







Unit: mm

# **RoHS Compliance and Lead Free Relay Information**

#### 1. General Information

- Relays produced after the specific date code that is indicated on each data sheet are lead-free now. All of our signal and power relays are lead-free. Please refer to Lead-Free Status Info. (http://www.fcai.fujitsu.com/pdf/LeadFreeLetter.pdf)
- Lead free solder paste currently used in relays is Sn-3.0Aq-0.5Cu. From February 2005 forward Sn-3.0Cu-Ni will be used for FTRB3 and FTR-B4 series relays.
- All signal and power relays also comply with RoHS. Please refer to individual data sheets. Relays that are RoHS compliant do not contain the 6 hazardous materials that are restricted by RoHS directive (lead, mercury, cadmium, chromium IV, PBB, PBDE).
- It has been verified that using lead-free relays in leaded assembly process will not cause any problems (compatible).
- "LF" is marked on each outer and inner carton. (No marking on individual relays).
- To avoid leaded relays (for lead-free sample, etc.) please consult with area sales office.

We will ship leaded relays as long as the leaded relay inventory exists.

#### 2. Recommended Lead Free Solder Profile

Recommended solder paste Sn-3.0Ag-0.5Cu and Sn-3.0 Cu-Ni (only FTR-B3 and FTR-B4 from February 2005)

#### **Reflow Solder condition**

#### Flow Solder condition:

Pre-heating: maximum 120°C Soldering: dip within 5 sec. at

260°C soler bath

#### Solder by Soldering Iron:

Soldering Iron

Temperature: maximum 360°C Duration: maximum 3 sec.

We highly recommend that you confirm your actual solder conditions

### 3. Moisture Sensitivity

Moisture Sensitivity Level standard is not applicable to electromechanical realys.

#### 4. Tin Whisker

SnAgCu solder is known as low riskof tin whisker. No considerable length whisker was found by our in-house

### 5. Solid State Relays

• Each lead terminal will be changed from solder plating to Sn plating and Nickel plating. A layer of Nickel plating is between the terminal and the Sn plating to avoid whisker.

#### **Fujitsu Components International Headquarter Offices**

Fujitsu Component Limited Gotanda-Chuo Building

3-5, Higashigotanda 2-chome, Shinagawa-ku

Tokyo 141, Japan Tel: (81-3) 5449-7010 Fax: (81-3) 5449-2626

Email: promothq@ft.ed.fujitsu.com

Web: www.fcl.fujitsu.com

North and South America

Fujitsu Components America, Inc. 250 E. Caribbean Drive Sunnyvale, CA 94089 U.S.A. Tel: (1-408) 745-4900 Fax: (1-408) 745-4970

Email: components@us.fujitsu.com

Web: http://www.fujitsu.com/us/services/edevices/components/

Fujitsu Components Europe B.V.

Diamantlaan 25 2132 WV Hoofddorp Netherlands Tel: (31-23) 5560910 Fax: (31-23) 5560950

Email: info@fceu.fujitsu.com

Web: emea.fujitsu.com/components/

**Asia Pacific** 

Fujitsu Components Asia Ltd. 102E Pasir Panjang Road

#01-01 Citilink Warehouse Complex

Singapore 118529 Tel: (65) 6375-8560 Fax: (65) 6273-3021 Email: fcal@fcal.fujitsu.com

Web: http://www.fujitsu.com/sg/services/micro/components/

©2009 Fujitsu Components America, Inc. All rights reserved. All trademarks or registered trademarks are the property of their respective owners.

iran.
iates res. Fujitsu Components America or its affiliates do not warrant that the content of datasheet is error free. In a continuing effort to improve our products Fujitsu Components America, Inc. or its affiliates reserve the right to change specifications/datasheets without prior notice. Rev. June 30, 2009