


## DC Reverse Current


## A-700ZF SPST N.O., 300 Amps, 28 VDC, Cutout Reverse Current

## Features:


- SPST N.O. Main Contacts
- 28 VDC
  - 200 Amps
  - High Reliability
  - Meets many requirements of MIL-R-6106







CONTACTOR CONFIGURATION



Notes:

Dimensions for this product are expressed in inches. Multiply values by 25.4 for millimeters.

PRODUCT SPECIFICATIONS	
Construction	Gasket Sealed, Vented
Main Contacts:	
Configuration	SPST N.O.
Voltage (Nominal)	28 VDC
Current (Resistive)	300 Amps
Main Contactor Coil:	
Duty Cycle	Continuous
Voltage (Nominal)	28 VDC
Pick-Up (APP or SW)	18 VDC Maximum
Drop-Out (APP or SW)	.5 - 7 VDC
Coil Current @ +25°C	.31 Amp
Differential Voltage Coil:	
Positive Drop-Out (+BAT, - CASE)	22 VDC Maximum
Differential Voltage Pick-Up Gen to BAT	.4 ±25 VDC
Unexcieted Bus Pick-Up (+Gen, -CASE)	18 - 24 VDC
Reverse Current Drop-Out (+BAT to GEN)	9 - 25 Amps
Weight Maximum	3.0 Lbs.

TYPICAL APPLICATION: Reverse current protection for 1000 ampere DC starter/generators and/or transformer rectifier units.

Contact Hartman for a detailed Theory of Operation.

For factory-direct application assistance, contact the HARTMAN product team at (419) 521-9500, Fax (419) 526-2749.

© 2004 by Tyco Electronics Corporation. All Rights Reserved. HARTMAN and TYCO are trademarks.

Catalog (web doc only)	Dimensions are in inches and
Revised 5-04	millimeters unless otherwise
	specified. Values in brackets
www.tycoelectronics.com	are metric equivalents.

Dimensions are shown for reference purposes only. Specifications subject to change. USA: 1-800-522-6752 Canada: 1-905-470-4425 Mexico: 01-800-733-8926 C. America: 52-55-5-729-0425 South America: 55-11-3611-1514 Hong Kong: 852-2735-1628 Japan: 81-44-844-8013 UK: 44-141-810-8967