

DESCRIPTION

The Accutek AK491024 high density memory module is a random access memory organized in 1 Meg x 9 bit words. The assembly consists of nine standard 1 Meg x 1 DRAMs in plastic leaded chip carriers (SOJ) mounted on the front side of a printed circuit board. The module can be configured as a leadless 30 pad SIM or a leaded 30 pin SIP. This packaging approach provides a 6 to 1 density increase over standard DIP packaging.

The operation of the AK491024 is identical to nine 1 Meg x 1 DRAMs. For the lower eight bits data input is tied to the data output and brought out separately for each device, with common \overline{RAS} , \overline{CAS} control. This common I/O feature dictates the use of early-write cycles to prevent contention of D and Q. Since the Write-Enable (WE) signal must always go low before \overline{CAS} in a write cycle, Read-Write and Read-Modify-Write operation is not possible. For the ninth bit, the data input (D₉) and the data output (Q₉) pins are brought out separately and controlled by a separate PCAS for that bit. Bit nine is generally used for parity.

FEATURES

- 1,048,576 x 9 bit organization
- Optional 30 Pad leadless SIM (Single In-Line Module) or 30 Pin leaded SIP (Single In-Line Package)
- JEDEC standard pinout
- Common \overline{CAS} and \overline{RAS} control for the lower eight bits
- Separate PCAS control for D₉ and Q₉
- CAS-before-RAS refresh


PIN NOMENCLATURE

DQ ₁ - DQ ₈	Data In / Data Out
D9	Data In 9
Q9	Data Out 9
A ₀ - A ₉	Address Inputs
CAS, PCAS	Column Address Strobe
RAS	Row Address Strobe
WE	Write Enable
Vcc	5v Supply
Vss	Ground
NC	No Connect
	•

MODULE OPTIONS

Leadless SIM: AK49102	4S
Leaded SIP: AK491024	G


AK491024S / AK491024G 1,048,576 Word x 9 Bit CMOS Dynamic Random Access Memory



- Power
 3.465 Watt Max Active (80 nSEC)
 2.97 Watt Max Active (100 nSEC)
 2.475 Watt Max Active (120 nSEC)
 49.5 mW Max Standby
- Operating free air temperature 0⁰C to 70⁰C
- Upward compatible with AK594096 and AK5916384
- Downward compatible with AK49256

SYMBOL

FUNCTIONAL DIAGRAM



PIN ASSIGNMENT

-	1	Vcc	16	DQ5
	2	CAS	17	A8
	3	DQ1	18	A9
1	4	A0	19	NC
+	5	A1	20	DQ6
	6	DQ2	21	WE
	7	A2	22	Vss
1	8	A3	23	DQ7
-	9	Vss	24	NC
	10	DQ3	25	DQ8
	11	A4	26	Q9
1	12	A5	27	RAS
	13	DQ4	28	PCAS
	14	A6	29	D9
	15	A7	30	Vcc

ORDERING INFORMATION

PART NUMBER CODING INTERPRETATION

Ρ/	ART NUMBER CODING INTERP	'R	Εī	۲A	Ш	Oľ		
Pos	sition	1	2	3	4	5	6	7
1	Product							
	AK = Accutek Memory							
2	Туре							
	4 = Dynamic RAM							
	5 = CMOS Dynamic RAM							
•	6 = Static RAM							
3	Organization/Word Width							
	1 = by 1 16 = by 16 4 = by 4 32 = by 32							
	8 = by 8 $36 = by 36$							
	9 = by 9							
4	Size/Bits Depth							
	64 = 64K $4096 = 4 MEG$							
	256 = 256K 8192 = 8 MEG 1024 = 1 MEG 16384 = 16 MEG							
5	Package Type							
U	G = Single In-Line Package (SIP)							
	S = Single In-Line Module (SIM)							
	D = Dual In-Line Package (DIP)							
	W = .050 inch Pitch Edge Connect Z = Zig-Zag In-Line Package (ZIP)							
6	Special Designation							
•	P = Page Mode							
	N = Nibble Mode							
	K = Static Column Mode							
	W = Write Per Bit Mode V = Video Ram							
7	Separator							
	- = Commercial 0 ⁰ C to +70 ⁰ C							
M = Military Equivalent Screened								
	(-55 ⁰ C to +125 ⁰ C) I = Industrial Temperature Tested							
	$(-45^{\circ}C \text{ to } +85^{\circ}C)$							
	X = Burned In							
8	Speed (first two significant digits)							
	DRAMS SRAMS 50 = 50 nS $8 = 8 nS$							
	60 = 60 nS $10 = 10 nS$							
	70 = 70 nS $12 = 12 nS$							
	80 = 80 nS 15 = 15 nS							

The numbers and coding on this page do not include all variations available but are show as examples of the most widely used variations. Contact Accutek if other information is required.

EXAMPLES:

AK491024SP-80

1 Meg x 9, 80 nSEC DRAM 30 pin SIM Configuration, Page Mode

AK491024GN-70

1 Meg x 9, 70 nSEC Dram 30 pin SIP Configuration, Nibble Mode




ACCUTEK MICROCIRCUIT CORPORATION BUSINESS CENTER at NEWBURYPORT 2 NEW PASTURE ROAD, SUITE 1 NEWBURYPORT, MA 01950-4054 VOICE: 978-465-6200 FAX: 978-462-3396 Email: sales@accutekmicro.com Internet: www.accutekmicro.com

MECHANICAL DIMENSIONS

```
Inches
```

8



Accutek reserves the right to make changes in specifications at any time and without notice. Accutek does not assume any responsibility for the use of any circuitry described; no circuit patent licenses are implied. Preliminary data sheets contain minimum and maximum limits based upon design objectives, which are subject to change upon full characterization over the specific operating conditions.