

NC500/500SM Series





Noise Modules for BITE

The NC500 (through hole) and NC500SM (surface mount) Series noise modules are an economical solution for built-in test requirements. They contain complete bias circuits and require no external components.

The surface mount package is suitable for mounting on microstrip. The modules produce extremely flat output power versus frequency characteristic that is insensitive to temperature and voltage variations.

The NC500 Series modules are housed in a TO-8 metal can, and require 0.2 to 5 mA, while the 500SM Series modules are housed in a surface mount plastic package. Both typically require 5 mA and produce a minimum of 31 dB ENR of white Gaussian noise. The NC510 and 510SM Series typically require 15 mA and have higher output with a minimum of 51 dB ENR.

Typical applications for these noise modules include built-in test equipment (BITE), signal strength meters for cellular, PCS, CATV, calibrators, spectrum analyzers, radar warning receivers (RWR), and dither A/D quantization error. Noise Com can optimize frequency range, voltage and output levels for specific applications. Most models are available from stock.

When ordering, add the suffix "SM" to the model number to denote the surface mount version. If the suffix is not included, the drop-in version will be supplied.

(Optional custom screening available)

Applications

- Built-in test equipment (BITE)
- Signal strength meters for cellular, PCs and CATV
- Calibrators
- Spectrum analyzers
- Radar warning receivers (RWR)
- Dither A/D quantization error
- Gain-bandwidth product testing


Model For	Model For	Model For	Frequency	Minimur	n Output	Output	I (Max)
+12 V Supply	+15 V Supply	+28 V Supply	Range	ENR (dB)) @ R _ι (Ω)	Flatness (dB)	(mA)
NC501/12	NC501/15	NC501	200 kHz - 500 MHz	31	50	±0.5	10
NC502/12	NC502/15	NC502	200 kHz - 1 GHz	31	50	±1.0	10
NC503/12	NC503/15	NC503	200 kHz - 2 GHz	31	50	±1.5	10
NC504/12	NC504/15	NC504	200 kHz - 3 GHz	31	50	±1.5	10
NC505/12	NC505/15	NC505	200 kHz - 4 GHz	31	50	±2.0*	10
NC506/12	NC506/15	NC506	200 kHz - 5 GHz	31	50	±2.5*	10
NC511/12	NC511/15	N/A	200 kHz - 500 MHz	51	50	±2.0	30
NC512/12	NC512/15	N/A	200 kHz - 1 GHz	51	50	±2.0	30
NC513/12	NC513/15	N/A	200 kHz - 2 GHz	51	50	±2.0	30

^{1.} Military version in compliance with MIL-E-5400T Class 2 (add suffix M). Not available in surface mount, NC501 to NC506 Series only.


Specifications

Output	White Gaussian noise			
Minimum power output	31 dB ENR (-143 dBm/Hz) 51 dB			
	ENR (-123 dBm/Hz)			
Crest factor	5:1			
Supply current	0.2 to 5 mA(NC500 Series) 10 to			
	20 mA (NC510 Series)			
Temperature coefficient	0.01 dB/°C			
Supply sensitivity	0.1 dB/%ÆV			
Operating temperature	0° C to +70° C (surface mount)			
	-55° C to 85° C (drop-in)			
Storage temperature	-65° to +150° C			
Packaging	Drop-in or surface mount			
Power	+12, +15 V or +28 V			
Absolute maximum input voltage	+30 V for +15 V models +40 V for			
	+28 V models			

NC500 Series Dimensions (inches)



NC500SM Series Dimensions (inches)



Wireless Telecom Group Inc. 25 Eastmans Rd

25 Eastmans Rd Parsippany, NJ 07054

Sales Offices

Parsippany, NJ United States

Tel: +1 973 386 9696 Fax: +1 973 386 9191 www.noisecom.com

Cheadle Hulme, Cheshire United Kingdom

Tel: +44 (0) 161 486 3353 Fax: +44 (0) 161 486 3354

Roissy France

Tel: +33 (0) 1 72 02 30 30 Fax: +33 (0) 1 49 38 01 06

Ismaning Germany

Tel: +49 (0) 89 996 41 0 Fax: +49 (0) 89 996 41 440

Singapore

Tel: +65 6827 9670 Fax: +65 6827 9601

Shanghai China

Tel: +86 21 5835 5718 Fax: +86 21 5835 5238

© Copyright 2008 All rights reserved.

NC/NC500/0908/EN Note: Specifications, terms and conditions are subject to change without prior notice.



^{2.} Add SM for surface mount. Otherwise TO-8 is standard.

^{*} Flatness ±4.0 for SM Series of these models.