

FM SPECIFICATIONS

Part no.	V _R -max (V)	Capacitance (pF)					Capacitance Ratio				Series Resistance (max.)	Pkg
		min.	typ	max	V _R	ΔCmax	min	typ	max	V _R (V)		
KV1300NT	18	69.13	74.37	79.61	2		2.1	2.35	2.6	3/8	0.5Ω	T092-3
		57.71		3								
		33.56		6								
		23.83		8								
KV1310A-2	18	41.40		46.16	2	3%	2.0		2.6	2/8	0.5Ω	CB2-6
		26.26		4	3%							
		19.13		6	3%							
		16.01		8	3%							
KV1310A-3	18	41.40		46.16	2	3%	2.0		2.6	2/8	0.5Ω	CB3-9
		26.26		4	3%							
		19.13		6	3%							
		16.01		8	3%							
KV1310NT	18	41.33		46.29	2		2.2		2.42	2/8	0.5Ω	T092-3
		26.49		4								
		19.24		6								
		16.05		8								
KV1320N	30	39.79		46.16	7		2.57	2.8	3.03	7/25	0.5Ω	T092-3
		24.25		13								
		17.32		19								
		13.93		25								
KV1330A-1	18	69.30		78.80	2		3.7		5.0	2/9	0.5Ω	CB1-3
		43.05		4								
		25.20		6								
		15.35		9								
KV1330A-2	18	69.30		78.80	2	3%	3.7		5.0	2/9	0.5Ω	CB2-6
		43.05		4	3%							
		25.20		6	3%							
		15.35		9	3%							
KV1330NT	18	69.14		77.43	2		3.7		5.0	2/9	0.5Ω	T092-3
		43.09		3								
		25.05		6								
		15.44		9								
KV1350NT	18	59.15	62.50	65.90	1		4.6			1/9	Q min: 60, 3V, 100MHz	T092-3
		17.67		6								
		10.77		9								
KV1360NT	18	86.10	92.00	98.00	1		4.7			1/6.5	0.6Ω	T092-3
				2								
				3								
		13.90		4.5								
KV1362A-1	18	86.10	92.00	98.00	1		4.7			1/6.5	0.6Ω	CB1-2
				2								
				3								
		13.90		4.5								