

8700 E. Thomas Road Scottsdale, AZ 85252 Phone: (480) 941-6300 Fax: (480) 947-1503

## **Features**

- For surface mount applications (flat handling surface for accurate placement)
- 3.3 thru 100 Volt Voltage Range
- High Surge Current Rating
- Higher Voltages Available
- Electrically Equivalent to JEDEC Registered 1N4728A thru 1N4764A
- Available on Tape and Reel.

# **Mechanical Data**

- Package similar to JEDEC DO-214AC (see dimension 'A' note)
- Terminals solderable per MIL-STD-750, Method 2026
- Polarity is indicated by cathode band.
- Maximum temperature for soldering: 260°C for 10 seconds.
- For surface mount applications with flame retardent epoxy meeting UL94V-0

## Maximum Ratings @ 25°C Unless Otherwise Specified

Maximum Forward Voltage	$V_{F}$	1.2V	(Note: 1)
Peak Surge Current	ls	See Table 1	
Steady State Power Dissipation	P <sub>(AV)</sub>	2.0W	(Note: 2,3)
Operating And	(,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,		
Storage	$T_J, T_{STG}$	-55°C to	
Temperatures		+150°C	
Thermal Resistance	$R_{ ext{ heta}JL}$	25°C/W	

## NOTES:

- 1. Forward Current @ 200mA.
- 2. Mounted on 4.0mm<sup>2</sup> copper pads to each terminal.
- 3. Lead temperature at 100 °C or less. Derate linearly above 100 °C to zero power at 150 °C.

# SILICON

**SMAJ4728A** 

THRU

**SMAJ4764A** 

# 2 WATT ZENER DIODES



	INCHES		ММ		
DIM	MIN	MAX	MIN	MAX	NOTE
Α	.078	.115	1.98	2.92	1
В	.052	.058	1.32	1.47	
С		.005		.127	
D		.02		.51	
Е	.030	.060	.76	1.52	
F	.055	.075	1.65	2.13	
G	.194	.216	4.93	5.48	
Н	.160	.180	3.99	4.50	
J	.100	.110	2.57	2.79	

NOTE 1: THIS MAXIMUM DIMENSION IS LARGER THAN THE STANDARD JEDEC CALL OUT. STANDARD JEDEC IS 105 INCHES OR 2.66 MM.





## SMAJ4728A thru SMAJ4764A

## Electrical Characteristics @ 25°C Unless Otherwise Specified

PART NUMBER	ZENER VOLTAGE (Vz) (NOTE 4)	TEST CURRENT (Izt)	MAXIMUM DYNAMIC IMPEDANCE (Zzt @ Izt)	MAXIMUM REVERSE CURRENT (IR @ VR)	TEST VOLTAGE (Vr)	MAXIMUM REGULATOR CURRENT (Izm) TL = 100°C	MAXIMUM KNEE IMPEDANCE (Zzk @ Izk)	TEST CURRENT (Izκ)	MAXIMUM (SURGE) CURRENT (Is)
	VOLTS	mA	OHMS	μΔ	VOLTS	MA	OHMS	mA	m A
SMA.14728A	3.3	76	10	100	1	552	400	1.0	1380
SMA.14729A	3.6	69	10	100	1	504	400	1.0	1260
SMA.14730A	3.9	64	9	50	1	468	400	1.0	1190
SMAJ4731A	4.3	58	9	10	1	434	400	1.0	1070
SMA.14732A	4 7	53	8	10	1	386	500	1.0	970
SMA.J4733A	5.1	49	7	10	1	356	550	1.0	890
SMA.J4734A	5.6	45	5	10	2	324	600	1.0	810
SMAJ4735A	6.2	41	2	10	3	292	700	1.0	730
SMA.J4736A	6.8	37	3.5	10	4	266	700	1.0	660
SMAJ4737A	7.5	34	4.0	10	5	242	700	0.5	605
SMAJ4738A	8.2	31	4.5	10	6	220	700	0.5	550
SMAJ4739A	9.1	28	5.0	10	7	200	700	0.5	500
SMAJ4740A	10	25	7	10	7.6	182	700	0.25	454
SMAJ4741A	11	23	8	5	8.4	166	700	0.25	414
SMAJ4742A	12	21	9	5	9.1	152	700	0.25	380
SMAJ4743A	13	19	10	5	9.9	138	700	0.25	344
SMAJ4744A	15	17	14	5	11.4	132	700	0.25	304
SMAJ4745A	16	15.5	16	5	12.2	114	700	0.25	285
SMAJ4746A	18	14	20	5	13.7	100	750	0.25	250
SMAJ4747A	20	12.5	22	5	15.2	90	750	0.25	225
SMAJ4748A	22	11.5	23	5	16.7	82	720	0.25	205
SMAJ4749A	24	10.5	25	5	18.2	76	750	0.25	190
SMAJ4750A	27	9.5	35	5	20.6	68	750	0.25	170
SMAJ4751A	30	8.5	40	5	22.8	60	1000	0.25	150
SMAJ4752A	33	7.5	45	5	25.1	54	1000	0.25	135
SMAJ4753A	36	7.0	50	5	27.4	50	1000	0.25	125
SMAJ4754A	39	6.5	60	5	29.7	46	1000	0.25	115
SMAJ4755A	43	6.0	70	5	32.7	44	1500	0.25	110
SMAJ4756A	47	5.5	80	5	35.8	38	1500	0.25	95
SMAJ4757A	51	5.0	95	5	38.8	36	1500	0.25	90
SMAJ4758A	56	4.5	110	5	42.6	32	2000	0.25	80
SMAJ4759A	62	4.0	125	5	47.1	28	2000	0.25	70
SMAJ4760A	68	3.7	150	5	51.7	26	2000	0.25	65
SMAJ4761A	75	3.3	175	5	56.0	24	2000	0.25	60
SMAJ4762A	82	3.0	200	5	62.2	22	3000	0.25	55
SMAJ4763A	91	2.8	250	5	69.2	20	3000	0.25	50
SMAJ4764A	100	2.5	350	5	76.0	18	3000	0.25	45

#### NOTE:

The type numbers shown have a 5% tolerance on nominal zener voltage. No suffix signifies a 10% tolerance, C signifies 2%, and D signifies 1% tolerance.
The Zener impedance is derived from the 60 Hz ac voltage, which results when an ac current having an rms value equal to 10% of the dc Zener

current ( $I_{ZT}$  or  $I_{ZK}$ ) is superimposed on  $I_{ZT}$ . Zener impedance is measured at two points to insure a sharp knee on the breakdown curve and eliminate unstable units.

3. The reverse surge current is measured at 25 °C ambient using a 'square wave or equivalent sine wave pulse 1/120 second duration superimposed on I<sub>ZT</sub>.

4. Voltage at thermal equilibrium or 90 seconds after application of dc current.

This datasheet has been download from:

www.datasheetcatalog.com

Datasheets for electronics components.

	nicrosemi.com/p	obpolicy.asp		G	ìo					
<b>v</b>			~							
				bout		NEWS		Contor EMI	PLOYME	NT HOME
		-	keyword			Г	par	t number		Г
			Search:			Γ	1	Sedi Cit:		<u></u> _
	) Sa	ales Contacts						Careers		Investors
i	· · ·			1						
RoHS/Pb-FREEPO	<u>DLICY</u>									
<u>RoHS/Pb-FREEPC</u>   <u>RoHS/Pb-FREECC</u>   <u>MSCCOLORADO</u>	DLICY ONTACTS 2									
<u>RoHS/Pb-FREEPC</u>   <u>RoHS/Pb-FREECC</u>   <u>MSCCOLORADO</u>   <u>MSCIP</u>	<u>DLICY</u> <u>ONTACTS</u> <u>D</u>									
RoHS/Pb-FREEPC   RoHS/Pb-FREECC   MSCCOLORADO   MSCIP   MSCLAWRENCE	DLICY ONTACTS 2									
RoHS/Pb-FREEPC   RoHS/Pb-FREECC   MSCCOLORADO   MSCIP   MSCLAWRENCE   MSCLOWELL	DLICY ONTACTS 2									
R₀HS/Pb-FREEP(               MSCCOLORADO         MSCLAWRENCE   	DLICY ONTACTS 2 2 LE									
RoHS/Pb-FREEP(   RoHS/Pb-FREEC(   MSCCOLORADO   MSCLOREL   MSCLAWRENCE   MSCLOWELL   MSCLOWELL	DLICY ONTACTS 2 E LE	MSG	C PPG - S	witchi	ng					
RoHS/Pb-FREEP(   RoHS/Pb-FREEC(   MSCCOLORADO   MSCCIP   MSCLAWRENCE   MSCLOWELL   MSCSCOTTSDAL	DLICY ONTACTS 2 : LE	<u>MS</u>	C PPG - S C PPG - N	witchi	ng					

Microsemi Corporation (MSC) is committed to manage its business in an environmentally responsible manner and Microsemi has RoHS and Pb-free initiatives to support those customers that require RoHS compliant and/or Pb-free products.

Most plastic encapsulated products will be transitioned to a Pb-free finish and also use mold compounds that are RoHS compliant for a 260C reflow temperature. For additional information regarding Pb-free or RoHS compliant products, the customer should contact the <u>Microsemi</u> <u>Division</u> that provides that product.



Hermetic military products manufactured by Microsemi are processed in accordance with requirements specified by MIL-PRF-19500, MIL-PRF-38534 and MIL-PRF-38535. These requirements do not allow termination finishes that are Pb-free or RoHS compliant. If RoHS compliant hermetic products for equivalent commercial part numbers are required, the customer should contact the applicable <u>Microsemi Division</u>.

In the case of Plastic Encapsulated and Commercial Hermetic packages, Microsemi may offer two versions of a product where one version will be RoHS compliant and the other will not be compliant. In those examples, the RoHS compliant version will include an "e#" designator as a suffix to the Part Number indicating the Pb-free 2nd level interconnect terminal finish category defined in JESD97. In these offerings, the most frequent terminal finish is pure Tin and the suffix of the part number is "e3".

Microsemi Corporation ("**MSC**") is committed to support those customers requiring RoHS and/or Pb-free (Lead free) compliant components. The term Pb-free (Lead-free) is defined in JESD97 and applies to components in which the Lead (Pb) level in any of the raw materials and the end product

is less than or equal to 0.1% by weight and also meets any Pb-free requirements/definitions adopted by the RoHS Directive 2002/95/EC. The RoHS term is an acronym for European Directive, *Restriction of the Use of Certain Hazardous Substances in Electrical and Electronic Equipment*. This also means a component with Pb-free termination finish compatible with Pb-free soldering processes. The RoHS compliant components may include Pb in the internal high melting type solder connections or glass materials of the component as defined in the exemptions of the RoHS European Directive.

Although the RoHS directive requires the use of Pb-free lead finish and solder processes, there has been a historical concern about the growth of Tin whiskers when using these Pb-free processes. The most common Pb-free lead finish currently being used is 100% Matte Tin (Sn) and several IC manufacturers have shown that this lead finish is much less prone to whisker formation than older bright tin finishes. Microsemi will provide the reliability and tin whisker growth data that has been taken on its products. However, tin whisker growth is dependent on the environment that is seen by the product. Customers are encouraged to collect their own reliability data and perform a risk assessment based their individual requirements. For general information on tin whiskers please see the following sites;

NASA website on Tin whiskers: <u>Nasa</u> NEMI Tin whisker activities <u>NEMI</u> CALCE Tin Whisker Working Group <u>CALCE</u>

## **Important Information Disclaimer:**

MSC represents and warrants that the information provided herein is to the best of its knowledge and belief accurate as of the date that it was provided. MSC bases such knowledge and belief on information provided by third parties, and MSC makes no representation or warranty as to the accuracy of such third party information. MSC has taken and will continue to take, reasonable steps to provide representative and accurate information to its Customers, but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. Certain MSC suppliers consider "material content" to be Confidential Information and thereby proprietary, whereby CAS numbers for such materials may not be available for release to Customers. MSC shall not be liable for loss of use, revenue, profit, or for any special, incidental, or consequential damages arising out of, connected with, or resulting from, the information provided in such Questionnaire, or otherwise; and in no event shall MSC's direct liability arising out of, connected with, or resulting from such information exceed the purchase price of the semiconductor component(s) referenced in such Questionnaire that MSC sold to the Customer during the three (3) months immediately prior to the date of such Questionnaire.

Privacy Policy | Site Map | Terms & Conditions

### PPG Webex Portal | PPG Extranet Login

<u>Avionics | Backlight Inverters | L-Band Radar | LED Driver | LDMOS & VDMOS | MOSFETs, IGBTs, & Diodes | Pin Diodes | Power Modules</u>

<u>RF Power & Bipolar Transistors | S-Band Radar | SCR | Thyristors | Varacter Diode | WLAN Power Amplifier | Zener</u> <u>Diode | Power Over Ethernet | IEEE802.3af | PoE ICs</u>

Copyright © 2010 Microsemi Corporation. All rights reserved. The Endwave logo is a registered trademark of Endwave Corporation.