

---

# **HD74LVC534**

Octal D-type Flip Flops with 3-state Outputs

**HITACHI**

ADE-205-071B(Z)

Rev.2

September 1995

---

## **Description**

The HD74LVC534 has eight edge trigger D type flip flops with three state outputs in a 20 pin package. Data at the D inputs meeting set up requirements, are transferred to the Q outputs on positive going transitions of the clock input. When the latch enable goes low, data at the D inputs will be retained at the outputs until latch enable returns high again. When a high logic level is applied to the output control input, all outputs go to a high impedance state, regardless of what signals are present at the other inputs and the state of the storage elements. Low voltage and high speed operation is suitable at the battery drive product (note type personal computer) and low power consumption extends the life of a battery for long time operation.

## **Features**

- $V_{cc} = 2.0 \text{ V to } 5.5 \text{ V}$
- All inputs  $V_{ih} (\text{Max.}) = 5.5 \text{ V} (@V_{cc} = 0 \text{ V to } 5.5 \text{ V})$
- Typical  $V_{ol}$  ground bounce < 0.8 V ( $@V_{cc} = 3.3 \text{ V}, Ta = 25^\circ\text{C}$ )
- Typical  $V_{oh}$  undershoot > 2.0 V ( $@V_{cc} = 3.3 \text{ V}, Ta = 25^\circ\text{C}$ )
- High output current  $\pm 24 \text{ mA} (@V_{cc} = 3.0 \text{ V to } 5.5 \text{ V})$

---

## HD74LVC534

---

### Function Table

Inputs			Output $\bar{Q}$
$\bar{G}$	CK	D	
H	X	X	Z
L	$\uparrow$	L	H
L	$\uparrow$	H	L
L	L	X	$Q_0$

H : High level

L : Low level


X : Immaterial

Z : High impedance

$\uparrow$  : Low to high transition

$Q_0$  : Level of  $\bar{Q}$  before the indicated steady input conditions were established.

### Pin Arrangement



### Absolute Maximum Ratings

Item	Symbol	Ratings	Unit	Conditions
Supply voltage	$V_{cc}$	−0.5 to 6.0	V	
Input diode current	$I_{ik}$	−50	mA	$V_i = -0.5\text{ V}$
Input voltage	$V_i$	−0.5 to 6.0	V	
Output diode current	$I_{ok}$	−50	mA	$V_o = -0.5\text{ V}$
		50	mA	$V_o = V_{cc} + 0.5\text{ V}$
Output voltage	$V_o$	−0.5 to $V_{cc} + 0.5$	V	
Output current	$I_o$	±50	mA	
$V_{cc}$ , GND current / pin	$I_{cc}$ or $I_{GND}$	100	mA	
Storage temperature	Tstg	−65 to +150	°C	

Note: The absolute maximum ratings are values which must not individually be exceeded, and furthermore, no two of which may be realized at the same time.

### Recommended Operating Conditions

Item	Symbol	Ratings	Unit	Conditions
Supply voltage	$V_{cc}$	1.5 to 5.5	V	Data retention
		2.0 to 5.5	V	At operation
Input / output voltage	$V_i$	0 to 5.5	V	$\bar{G}$ , CK, D
	$V_o$	0 to $V_{cc}$	V	$\bar{Q}$
Operating temperature	Ta	−40 to 85	°C	
Output current	$I_{oh}$	−12	mA	$V_{cc} = 2.7\text{ V}$
		−24 <sup>12</sup>	mA	$V_{cc} = 3.0\text{ V to }5.5\text{ V}$
	$I_{ol}$	12	mA	$V_{cc} = 2.7\text{ V}$
		24 <sup>12</sup>	mA	$V_{cc} = 3.0\text{ V to }5.5\text{ V}$
Input rise / fall time <sup>11</sup>	$t_r, t_f$	10	ns/V	

Notes: 1. This item guarantees maximum limit when one input switches.

Waveform : Refer to test circuit of switching characteristics.

2. duty cycle ≤ 50%

---

## HD74LVC534

---

### Electrical Characteristics


Item	Symbol	$V_{cc}$ (V)	Ta = -40 to 85°C			
			Min	Max	Unit	Test Conditions
Input voltage	$V_{IH}$	2.7 to 3.6	2.0	—	V	
		4.5 to 5.5	$V_{cc} \times 0.7$	—	V	
	$V_{IL}$	2.7 to 3.6	—	0.8	V	
		4.5 to 5.5	—	$V_{cc} \times 0.3$	V	
Output voltage	$V_{OH}$	2.7 to 5.5	$V_{cc} - 0.2$	—	V	$I_{OH} = -100 \mu A$
		2.7	2.2	—	V	$I_{OH} = -12 mA$
		3.0	2.4	—	V	
		3.0	2.0	—	V	$I_{OH} = -24 mA$
		4.5	3.8	—	V	
	$V_{OL}$	2.7 to 5.5	—	0.2	V	$I_{OL} = 100 \mu A$
		2.7	—	0.4	V	$I_{OL} = 12 mA$
		3.0	—	0.55	V	$I_{OL} = 24 mA$
		4.5	—	0.55	V	
	$I_{IN}$	0 to 5.5	—	$\pm 5.0$	$\mu A$	$V_{IN} = 5.5 V$ or GND
Off state output current	$I_{OZ}$	5.5	—	$\pm 10$	$\mu A$	$V_{IN} = V_{cc}$ , GND $V_{OUT} = V_{cc}$ or GND
Quiescent supply current	$I_{cc}$	5.5	—	20	$\mu A$	$V_{IN} = V_{cc}$ or GND
	$\Delta I_{cc}$	3.0 to 3.6	—	500	$\mu A$	$V_{IN} =$ one input at $(V_{cc} - 0.6)V$ , other inputs at $V_{cc}$ or GND

## Switching Characteristics


Item	Symbol	$V_{cc}$ (V)	Ta = -40 to 85°C			Unit	From (Input)	To (Output)
			Min	Typ	Max			
Maximum clock frequency	$f_{max}$	2.7	80.0	—	—	MHz		
			3.3±0.3	100.0	150.0	—		MHz
			5.0±0.5	125.0	—	—		MHz
Propagation delay time	$t_{PLH}$	2.7	—	7.0	9.5	ns	CK	$\bar{Q}$
	$t_{PHL}$	3.3±0.3	1.5	5.5	8.5	ns		
		5.0±0.5	—	4.0	7.0	ns		
Output enable time	$t_{ZH}$	2.7	—	7.0	9.5	ns	$\bar{G}$	$\bar{Q}$
	$t_{ZL}$	3.3±0.3	1.5	5.5	8.5	ns		
		5.0±0.5	—	4.0	7.0	ns		
Output disable time	$t_{HZ}$	2.7	—	5.0	8.5	ns	$\bar{G}$	$\bar{Q}$
	$t_{LZ}$	3.3±0.3	1.5	4.5	7.5	ns		
		5.0±0.5	—	3.5	6.5	ns		
Setup time	$t_{su}$	2.7	2.0	—	—	ns		
		3.3±0.3	2.0	—	—	ns		
		5.0±0.5	2.0	—	—	ns		
Hold time	$t_h$	2.7	1.5	—	—	ns		
		3.3±0.3	1.5	—	—	ns		
		5.0±0.5	1.5	—	—	ns		
Pulse width	$t_w$	2.7	4.0	—	—	ns		
		3.3±0.3	4.0	—	—	ns		
		5.0±0.5	3.0	—	—	ns		
Input capacitance	$C_{IN}$	2.7	—	3.0	—	pF		
Output capacitance	$C_o$	2.7	—	15.0	—	pF		

# HD74LVC534


## Test Circuit




## Waveforms – 1



**Waveforms – 2**



**Waveforms – 3**



## Notice

When using this document, keep the following in mind:

1. This document may, wholly or partially, be subject to change without notice.
2. All rights are reserved: No one is permitted to reproduce or duplicate, in any form, the whole or part of this document without Hitachi's permission.
3. Hitachi will not be held responsible for any damage to the user that may result from accidents or any other reasons during operation of the user's unit according to this document.
4. Circuitry and other examples described herein are meant merely to indicate the characteristics and performance of Hitachi's semiconductor products. Hitachi assumes no responsibility for any intellectual property claims or other problems that may result from applications based on the examples described herein.
5. No license is granted by implication or otherwise under any patents or other rights of any third party or Hitachi, Ltd.
6. MEDICAL APPLICATIONS: Hitachi's products are not authorized for use in MEDICAL APPLICATIONS without the written consent of the appropriate officer of Hitachi's sales company. Such use includes, but is not limited to, use in life support systems. Buyers of Hitachi's products are requested to notify the relevant Hitachi sales offices when planning to use the products in MEDICAL APPLICATIONS.