



SCHOTTKY BARRIER RECTIFIERS


VOLTAGE 40 to 200 Volts CURRENT 2.0 Amperes

FEATURES

- Plastic package has Underwriters Laboratory Flammability Classification 94V-O utilizing Flame Retardant Epoxy Molding Compound.
- Exceeds environmental standards of MIL-S-19500/228
- For use in low voltage, high frequency inverters , free wheeling , and polarity protection applications.
- Lead free in compliance with EU RoHS 2011/65/EU directive

MECHANICAL DATA

- · Case: DO-15 Molded plastic
- Terminals: Axial leads, solderable per MIL-STD-750, Method 2026
- · Polarity: Color band denotes cathode
- Mounting Position: Any
- · Weight: 0.014 ounces, 0.397 grams



MAXIMUM RATINGS

Ratings at 25°C ambient temperature unless otherwise specified. Single phase, half wave, 60 Hz, resistive or inductive load.

PARAMETER	SYMBOL	MBR240	MBR245	MBR250	MBR260	MBR280	MBR290	MBR2100	MBR2150	MBR2200	UNITS
Maximum Recurrent Peak Reverse Voltage	V _{RRM}	40	45	50	60	80	90	100	150	200	V
Maximum RMS Voltage	V _{RMS}	28	31.5	35	42	56	63	70	105	140	V
Maximum DC Blocking Voltage	V _{DC}	40	45	50	60	80	90	100	150	200	V
Maximum Average Forward Rectified Current .375"(9.5mm) lead length (see fig1)	I _{F(AV)}	2.0						А			
Peak Forward Surge Current : 8.3ms single half sine- wave superimposed on rated load(JEDEC method)	I _{FSM}	50						А			
Typical Thermal Resistance (Note 2)	R _{eJA}	35						°C / W			
Maximum Forward Voltage at 2.0A (Note 1)	V _F	0.7		0.74		0.8		0.9		V	
Maximum DC Reverse Current at T _J =25°C Rated DC Blocking Voltage T _J =100°C	I _R	0.05 20					mA				
Operating Junctionand Storage Temperature Rang	T _J ,T _{STG}	-55 to +150 -65 to +175					°C				

NOTES:

1.Pulse Test: 300µs pulse with, 1% Duty Cycle.

2Thermal resistance junction to lead P.C.B mounted 0.375"(9.5mm) lead length.





RATING AND CHARACTERISTIC CURVES




Fig.1- FORWARD CURRENT DERATING CURVE




Fig.2- MAXIMUM NON-REPETITIVEPEAKFORWARD SURGE CURRENT




Fig.3-TYPICAL REVERSE CHARACTERISTIC




Fig.4- TYPICAL INSTANTANEOUS FORWARD CHARACTERISTIC





Part No_packing code_Version

MBR240_AY_00001

MBR240_AY_10001


MBR240_B0_00001

MBR240_B0_10001

MBR240_R2_00001

MBR240_R2_10001

For example:



Packing Code XX					Version Code XXXXX					
Packing type	1 st Code	Packing size code	2 nd Code	HF or RoHS	1 st Code	2 nd ~5 th Code				
Tape and Ammunition Box (T/B)	Α	N/A	0	HF	0	serial number				
Tape and Reel (T/R)	R	7"	1	RoHS	1	serial number				
Bulk Packing (B/P)	В	13"	2							
Tube Packing (T/P)	Т	26mm	X							
Tape and Reel (Right Oriented) (TRR)	s	52mm	Y							
Tape and Reel (Left Oriented) (TRL)	L	PANASERT T/B CATHODE UP (PBCU)	U							
FORMING	F	PANASERT T/B CATHODE DOWN (PBCD)	D							





Disclaimer

- Reproducing and modifying information of the document is prohibited without permission from Panjit International Inc..
- Panjit International Inc. reserves the rights to make changes of the content herein the document anytime without notification. Please refer to our website for the latest document.
- Panjit International Inc. disclaims any and all liability arising out of the application or use of any product including damages incidentally and consequentially occurred.
- Panjit International Inc. does not assume any and all implied warranties, including warranties
 of fitness for particular purpose, non-infringement and merchantability.
- Applications shown on the herein document are examples of standard use and operation.
 Customers are responsible in comprehending the suitable use in particular applications.
 Panjit International Inc. makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.
- The products shown herein are not designed and authorized for equipments requiring high level of reliability or relating to human life and for any applications concerning life-saving or life-sustaining, such as medical instruments, transportation equipment, aerospace machinery et cetera. Customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Panjit International Inc. for any damages resulting from such improper use or sale.
- Since Panjit uses lot number as the tracking base, please provide the lot number for tracking when complaining.