

SPECIFICATION SHEET

JFW MODEL 75BT-013

BIAS TAP

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range	5-2150 MHz
Impedance	75 Ohms nominal
VSWR	1.25:1 maximum
Insertion Loss	0.4 dB maximum
DC Breakdown Voltage	50 Volts
DC Current Handling	1 Amp maximum
RF Input Power	1 Watt average
RF Connector	BNC, F, BNC or N (male or female)
DC Connector	Solder Terminal (.040")
Operating Temperature Range	-55°C to +85°C
Physical Size	See outline drawings: 092-2712 (F female/female) 092-4745 (N male/female)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
2324	03/13/2000	B		10791	03/09/2005	E	SL 03/09/2005
2334	03/21/2000	C		12277	12/29/2005	F	CLK 12/29/2005
9999	09/17/2002	D	SL 09/17/2002	20332	07/14/2011	G	TRS 07/14/2011