DATA IMAGE CORPORATION

LCD Module Specification

ITEM NO.: <u>TG322400FFNNB-01</u>

Table of Contents

1.	COVER & CONTENTS ·····	1
2.	RECORD OF REVISION ·····	2
3.	GENERAL SPECIFICATIONS ·····	3
4.	ABSOLUTE MAXIMUM RATINGS ·····	4
5.	ELECTRICAL CHARACTERISTICS ······	5
6.	ELECTRO-OPTICAL CHARACTERISTIC ······	5
7.	TIMING CHARACTERISTICS ······	7
8.	PIN CONNECTIONS ·····	9
9.	POWER SUPPLY ·····	9
10.	BLOCK DIAGRAM ·····	10
11.	QUALITY ASSURANCE ·····	11
12.	LOT NUMBERING SYSTEM ·····	16
13.	LCM NUMBERING SYSTEM ·····	16
14.	PRECAUTIONS IN USE LCM ······	17
15	OUTLINE DRAWING ·····	18
16.	PACKAGE INFORMATION	19

R&D Dept.	Q.C. Dept.	Eng. Dept.	Prod. Dept.
Alep	Toric	Hen	auf
Version:	Issued Date:	Sheet Code:	Total Pages:
В	2003/3/14		19

Rev	Date	Item	Page	Comment
в	MAR/14/03	13 11.2.3, 11.3,15	16 14-15,	New model numbering system updated from old P/N# TG32242FH 1.Change: 11.2.3 Inspection Parameters. 2.Add:11.3 Sampling Condition. 3. Modify: OUTLINE DRAWING.

2. RECORD OF REVISION

3. GENERAL SPECIFICATION

Display Format :	320 (\	N) ×	240 (H)	dots
Dots Pitch :	0.36 (\	N) ×	0.36 (H)	mm
Dots Size :	0.34 (\	N) ×	0.34 (H)	mm
View Area :	121 (\	N) ×	91.6 (H)	mm
General Dimensions :	150 (\	N) ×	106 (H) ×	2.7 (T) mm Max.
Weight :	g max.			
LCD Type :	STN Blue	STN	I Yellow V	FSTN
Polarizer mode :	Reflective	VTrar	sflective	
	Transmissive	Neg	ative	
View Angle :	V6 O'clock	<u>12 C</u>)'clock	Others
Backlight :	LED	EL		CCFL
Backlight Color :	Yellow green	Amt	ber	Blue Green
	White	Othe	ers	
Controller / Driver :	Msm6778/Msm6	779		
Temperature Range :	Normal Operating 0 t Storage -20	:o 50°C 0 to 70°C	Operatir	0

4. ABSOLUTE MAXIMUM RATINGS

4.1 ELECTRICAL ABSOLUTE MAXIMUM RATINGS

Vss=	0V, Ta	$= 25^{\circ}C$
Max	Llnit	

Item	Symbol	Min.	Max.	Unit
Supply Voltage (Logic)	VDD-VSS	-0.3	6.5	V
Supply Voltage (LCD Driver)	VDD-VEE	0	30	V
Input Voltage	VI	-0.3	VDD +0.3	V
Operating Temperature	Тор	-20	70	°C
Storage Temperature	Tstg	-30	80	°C

4.2 ENVIRONMENTAL ABSOLUTE MAXIMUM RATINGS

Item	Operating		Sto	rage	Comment	
nem	(Min.)	Max.)	(Min.)	(Max.)	Comment	
Ambient Temp	-20	70	-30	80	Note (1)	
Humidity	Note	e (2)	No	te(2)	Without Condensation	
Vibration		4.9M/S ²		19.6M/S ²	XYZ Direction	
Shock		29.4M/S ²		490M/S ²	XYZ Direction	

Note(1) Ta = $0^{\circ}C$: 50Hr Max.

Note(2) Ta $\leq 40^{\circ}$ C : 90% RH Max.

Ta $\geq 40^{\circ}$ C :

Absolute humidity must be lower than the humidity of 90% RH at 40°C.

Item	Symbol	Condition	Min.	Тур.	Max.	Unit
Supply Voltage (Logic)	VDD-VSS		4.5	5	5.5	V
		-20°C	26.2	26.7	27.2	
		-10°C	23	23.5	24	
Supply Voltage	VDD-Vo	0°C	21.9	22.4	22.9	
Supply Voltage (LCD)		10°C	21.2	21.7	22.2	V
		25°C	20.5	21.0	21.5	
		50°C	18.9	19.4	19.9	
		70°C	17.8	18.3	18.8	
Input Voltago	Vін		0.8*VDD		Vdd	V
Input Voltage	VIL]	VSS		0.2*VDD	v
Logic Supply	ldd	VDD-VSS=5V		3.6		mA
Current	IEE	VEE-VSS=-24V		3.0		ШA

5. ELECTRICAL CHARACTERISTICS

6. ELECTRO-OPTICAL CHARACTERISTICS

ITEM	Symbol	Condition	Min.	Тур.	Max.	Unit	Ref.
		-20°C		2000	3500	ms	
Rise Time	Tr	0°C		790	1300		
		25°C		200	400		Note (1)
		-20°C	-	1500	3000	ms	
Fall Time	Tf	0°C		670	1100		
		25°C		250	450		
Contrast	CR	25°C	4.0	6.0			Note (3)
	θ1~θ2	25°C &		60			Note (2)
View Angle	Ø1, Ø 2	CR≥2		50			Note (2)
Frame Frequency	Ff	25°C		78		Hz	


Note (1) & (2) : See next page

Note (3) : Contrast ratio is defined under the following condition:


CR= Brightness of non-selected condition Brightness of selected condition

- (a). Temperature ----- 25°C
- (b). Frame frequency ---- 78Hz
- (c). Viewing angle ----- θ = 0°, \emptyset = 0°
- (d). Operating voltage --- 21.0V


Note (1) Response time is measured as the shortest period of time possible between the change in state of an LCD segment as demonstrated below:




Condition:




- (b). Frame frequency ----- 78Hz
- (c). View Angle ----- $\theta = 0^\circ, \emptyset = 0^\circ$
- (d). Operating voltage ------ 21.0V









Page: 6 / 19


7. TIMING CHARACTERISTIC

Switching Characteristics

		(V _{DD}	=2.7 to 5.5 V,	Ta= -20 to	+75°C, CL:	=15 pF)
Parameter	Symbol	Condition	Min.	Тур.	Max.	Unit
10 ₁ , 10 ₆₁ (10 ₆₀ , 10 ₁₂₀)	t _{PLH}		*1		3	μs
"H", "L" Propagation Delay Time	t _{PHL}					
Clock Frequency	f _{CP}				1	MHz
CP Pulse Width	t _{WCP}		63	_		ns
Data Setup Time $IO_1, IO_{61} \rightarrow CP$ $(IO_{60}, IO_{120} \rightarrow CP)$	^t setu₽	_	100			ns
Data Hold Time $CP \rightarrow IO_1, IO_{61}$ $(CP \rightarrow IO_{60}, IO_{120})$	t _{HOLD}	<u> </u>	100			ns
CP Rise, Fall Time	t _{r (CP)} t _{f (CP)}		_		20	ns

*1 The relationship between ψ_{LH} (t_{PLH}) Min. and t_{HOLD} Min. satisfies the operation in a cascade connection state.


Note 1: When display is controlled by $\overline{\text{DISPOFF}}$ pin, CP rise and fall time must be $\leq 1 \, \mu$ s. Note 2: The above values are guaranteed when TCP is protected from light.




Switching Characteristics

Switching Characteris			(4.5≤	V _{DD} ≤5.5 V,	Ta=-20 to) +75°C)
Parameter	Symbol	Condition	Min.	Тур.	Max.	Unit
Clock Frequency	f _{CP}	DUTY=50%, V _{DD} =4.5 V	-	_	6.5	MHz
Clock Pulse Width	t _{W1}		56	_	_	ns
Load Pulse Width	t _{W2}		70			ns
Clock Pulse Rise/Fall Time	t _r , t _f				20	ns
Data Set-up Time	t _{DSU}		50		_	ns
Data Hold Time	t _{DHD}		40		_	ns
Clock Load Time 1	t _{CL1}	_	0			ns
Clock Load Time 2	t _{CL2}	_	65		_	ns
Load Clock Time 1	t _{LC1}		65		_	ns
Load Clock Time 2	t _{LC2}		65			ns
Propagation Delay Time	t _{PHL}	C _L =15 pF		_	236	ns
EIO1, EIO2 Set-up Time	t _{ESU}		50			ns
EIO ₁ , EIO ₂ Hold Time	t _{EHD}		50			ns

Note: The above values are quaranteed when TCP is protected from light.







8. PIN CONNECTIONS

NO	Symbol	Function
1	VO	Voltage input for LCD contrast
2	VEE	Negative Voltage input
3	D3	
4	D2	Data bus line
5	D1	Data bus line
6	D0	
7	NC	No connection
8	VSS	Ground (0V)
9	VDD	Logic power input
10	CP2	Data shift pulse.(CP)
11	CP1	Data latch pulse.(Load)
12	S	First line mark of common signal

9. POWER SUPPLY



10. BLOCK DIAGRAM



11. QUALITY ASSURANCE

11.1 Test Condition

11.1.1 Temperature and Humidity(Ambient Temperature)

Temperature	:	20 ± 5°C
Humidity	:	$65 \pm \mathbf{5\%}$

- 11.1.2 Operation Unless specified otherwise, test will be conducted with LCM in operation.
- 11.1.3 Container Unless specified otherwise, vibration test will be conducted on module only.
- 11.1.4 Test Frequency Single cycle.

11.1.5 Test Method

A. Thermal Cycle (Humid) Requirements

Samples f	Samples functionally tested at low humidity dwell in following profile:				
Ramp	31 deg C	88% RH	7 hours		
Dwell	31 deg C	88% RH	5 hours		
Ramp	41 deg C	59% RH	7 hours		
Dwell	41 deg C	59% RH	4 hours		
Loop 14 cycles					

B. Thermal Cycling (Non-Operating) Requirements

Fund	Functional test after entire test complete and 4 hours of stabilization.						
#1	Ramp	-25 deg C	15 min	#2	Ramp	-40 deg C	15 min
	Dwell	-25 deg C	80 min		Dwell	-40 deg C	80 min
	Ramp	70 deg C	30 min		Ramp	85 deg C	30 min
	Dwell	70 deg C	85 min		Dwell	85 deg C	85 min
	Ramp	25 deg C	15 min		Ramp	25 deg C	15 min
Loop 84 times - For First 3 days run profile #1.							
For remainder of test run profile #2							

C. Thermal Cycle (Operating) Requirements

Veri	fy functi	onality ever	y 3 days	of	4 units.					
#1	Ramp	-10 deg C	12 min	#2	Ramp	12 min	#3	Ramp	-30 deg C	12 min
	Dwell	-10 deg C	85 min		Dwell	85 min		Dwell	-30 deg C	85 min
	Ramp	60 deg C	25 min		Ramp	25 min		Ramp	70 deg C	25 min
	Dwell	60 deg C	91 min		Dwell	91 min		Dwell	70 deg C	91 min
	Ramp	25 deg C	15 min		Ramp	15 min		Ramp	25 deg C	15 min
Note	Note: LCDs not required to work at -30 deg C.									

D. Electrical Life Requirements

Functiona	al test done o	daily inside dwell of following profile:
Ramp	70 deg C	30 min
Dwell	70 deg C	324 hours
Ramp	25 deg C	30 min

E. Drop Requirements

48" to 1/2" steel plate all faces an	nd corners in the following order:
Sample 1 order of drop:	Sample 2 order of drop:
Corner - top right	Back (LCD up)
Corner - top left	Front (LCD down)
Corner - bottom right	Right face
Corner - bottom left	Left face
Top face	Bottom face
Bottom face	Top face
Left face	Corner - bottom left
Right face	Corner - bottom right
Front (LCD down)	Corner - top left
Back (LCD up)	Corner - top right
* Red is non-functional failure bo	Id is functional failure, data is from all four samples tested

* Red is non-functional failure, **bold** is functional failure - data is from all four samples tested


F. Vibration Requirements

FREQUENCY	10 TO 57 Hz
AMPLITUDE	0.075 mm
FREQUENCY	57 TO 500 Hz
ACCELERATION	9.8m/S ²
INTERVAL	10Hz-500Hz-10Hz/11min per cycle
DURATION	12 CYCLES IN EACH DIRECTION(X/Y/Z)


11.2 Inspection condition

11.2.1 Inspection conditions

The LCD shall be inspected under 40W white fluorescent light.



11.2.2 Definition of applicable Zones




A : Display Area

B : Non-Display Area

11.2.3 Inspection Parameters


No.	Parameter	Criteria
1	Black or White spots	$\begin{array}{ c c c c c }\hline \hline Zone & Acceptable & Class & AQL \\ \hline number & Of & Defects \\ \hline Dimension & A & B & Defects \\ \hline D < 0.15 & * & * & \\ \hline 0.15 \le D < 0.2 & 4 & 4 & \\ \hline 0.2 \le D \le 0.25 & 2 & 2 & \\ \hline D \le 0.3 & 0 & 1 & \\ \hline D = (Long + Short) / 2 & *: Disregard \\ \hline \end{array}$
2	Scratch, Substances	$\begin{tabular}{ c c c c c c c c c c c c c c c c c c c$
3	Air Bubbles (between glass & polarizer)	ZoneAcceptable numberClass of DefectsAQL
4	Uniformity of Pixel	0.25 < D 0 1 * : Disregard Total defects shall not excess 3/module. (1) Pixel shape (with Dent) 0.152




11.3 Sampling Condition

Unless otherwise agree in written, the sampling inspection shall be applied to the incoming inspection of customer. Lot size: Quantity of shipment lot per model. Sampling type: normal inspection, single sampling Inspection level: Level II Sampling table: MIL-STD-105E

12. LOT NUMBERING SYSTEM



13. LCM NUMBERING SYSTEM



14. PRECAUTION FOR USING LCM

1. LIQUID CRYSTAL DISPLAY (LCD)

LCD is made up of glass, organic sealant, organic fluid, and polymer based polarizers. The following precautions should be taken when handing,

(1). Keep the temperature within range of use and storage. Excessive temperature and humidity could cause

polarization degredation, polarizer peel off or bubble.

(2). Do not contact the exposed polarizers with anything harder than an HB pencil lead. To clean dust off the display surface, wipe gently with cotton, chamois or other soft material soaked in petroleum benzin.

(3). Wipe off saliva or water drops immediately. Contact with water over a long period of time may cause polarizer deformation or color fading, while an active LCD with water condensation on its surface will cause corrosion of ITO electrodes.

(4). Glass can be easily chipped or cracked from rough handling, especially at corners and edges.

(5). Do not drive LCD with DC voltage.

2. Liquid Crystal Display Modules

2.1 Mechanical Considerations

LCM are assembled and adjusted with a high degree of precision. Avoid excessive shocks and do not make any alterations or modifications. The following should be noted.

(1). Do not tamper in any way with the tabs on the metal frame.

(2). Do not modify the PCB by drilling extra holes, changing its outline, moving its components or modifying its pattern.

(3). Do not touch the elastomer connector, especially insert an backlight panel (for example, EL).

(4). When mounting a LCM make sure that the PCB is not under any stress such as bending or twisting . Elastomer contacts are very delicate and missing pixels could result from slight dislocation of any of the elements.

(5). Avoid pressing on the metal bezel, otherwise the elastomer connector could be deformed and lose contact, resulting in missing pixels.

2.2. Static Electricity

LCM contains CMOS LSI's and the same precaution for such devices should apply, namely

(1). The operator should be grounded whenever he/she comes into contact with the module. Never touch any of the conductive parts such as the LSI pads, the copper leads on the PCB and the interface terminals with any parts of the human body.

(2). The modules should be kept in antistatic bags or other containers resistant to static for storage.

(3). Only properly grounded soldering irons should be used.

(4). If an electric screwdriver is used, it should be well grounded and shielded from commutator sparks.

(5) The normal static prevention measures should be observed for work clothes and working benches; for the latter conductive (rubber) mat is recommended.(6). Since dry air is inductive to static, a relative humidity of 50-60% is recommended.

2.3 Soldering

(1). Solder only to the I/O terminals.

(2). Use only soldering irons with proper grounding and no leakage.

(3). Soldering temperature : $280^{\circ}C \pm 10^{\circ}C$

(4). Soldering time: 3 to 4 sec.

(5). Use eutectic solder with resin flux fill.

(6). If flux is used, the LCD surface should be covered to avoid flux spatters. Flux residue should be removed after wards.

2.4 Operation

(1). The viewing angle can be adjusted by varying the LCD driving voltage V0.

(2). Driving voltage should be kept within specified range; excess voltage shortens display life.

(3). Response time increases with decrease in temperature.

(4). Display may turn black or dark blue at temperatures above its operational range; this is (however not pressing on the viewing area) may cause the segments to appear "fractured".


(5). Mechanical disturbance during operation (such as pressing on the viewing area) may cause the segments to appear "fractured".

2.5 Storage

If any fluid leaks out of a damaged glass cell, wash off any human part that comes into contact with soap and water. Never swallow the fluid. The toxicity is extremely low but caution should be exercised at all the time.

2.6 Limited Warranty

Unless otherwise agreed between DATA IMAGE and customer, DATA IMAGE will replace or repair any of its LCD and LCM which is found to be defective electrically and visually when inspected in accordance with DATA IMAGE acceptance standards, for a period on one year from date of shipment. Confirmation of such date shall be based on freight documents. The warranty liability of DATA IMAGE is limited to repair and/or replacement on the terms set forth above. DATA IMAGE will not responsible for any subsequent or consequential events.



15 OUTLINE DRAWING

