



2FCS





2FCS-20-SG



PART No. & POSITIONS	DIMENSIONS	
	A	B
2FCS-20	.992 [25.10]	.709 [18.00]
2FCS-22	1.071 [27.20]	.787 [20.00]
2FCS-24	1.150 [29.20]	.866 [22.00]
2FCS-26	1.228 [31.00]	.945 [24.00]
2FCS-34	1.543 [39.20]	1.260 [32.00]
2FCS-36	1.622 [41.20]	1.339 [34.00]
2FCS-40	1.780 [45.10]	1.496 [38.00]
2FCS-44	1.937 [49.20]	1.654 [42.00]
2FCS-50	2.773 [55.10]	1.890 [48.00]
2FCS-60	2.567 [65.20]	2.283 [58.00]
2FCS-68	2.882 [73.20]	2.598 [66.00]

2FTR



2FTR-20-T

PART No. & POSITIONS	DIMENSIONS	
	A	B
2FTR-08	.480 [12.20]	.236 [6.00]
2FTR-10	.559 [14.20]	.315 [8.00]
2FTR-12	.637 [16.20]	.3937 [10.00]
2FTR-14	.716 [18.20]	.472 [12.00]
2FTR-16	.795 [20.20]	.551 [14.00]
2FTR-20	.952 [24.20]	.629 [16.00]
2FTR-22	1.031 [26.20]	.708 [18.00]
2FTR-24	1.110 [28.20]	.866 [22.00]
2FTR-26	1.189 [30.20]	.945 [24.00]
2FTR-34	1.503 [38.20]	1.260 [32.00]
2FTR-40	1.740 [44.20]	1.496 [38.00]
2FTR-44	1.897 [48.20]	1.654 [42.00]
2FTR-50	2.133 [54.20]	1.890 [48.00]
2FTR-68	2.842 [72.20]	2.598 [66.00]

Recommended PCB Layout