

S852TF


Vishay Semiconductors

Silicon NPN Planar RF Transistor

Description

The main purpose of this bipolar transistor is broadband amplification up to 2 GHz. In the space-saving 3-pin surface-mount SOT-490 package electrical performance and reliability are taken to a new level covering a smaller footprint on PC boards than previous packages.

In addition to space savings, the SOT-490 provides a higher level of reliability than other 3-pin packages, such as more resistance to moisture.



Due to the short length of its leads the SOT-490 is also reducing package inductances resulting in some better electrical performance. All of these aspects make this device an ideal choice for demanding RF applications.

Features

- · Low supply voltage
- Low current consumption
- Low noise figure
- 50 Ω input impedance at 945 MHz
- High power gain
- Lead (Pb)-free component
- Component in accordance to RoHS 2002/95/EC
 and WEEE 2002/96/EC

Applications

For low noise and high gain broadband amplifiers at collector currents from 0.2 mA to 5 mA.

Mechanical Data

Typ: S852TF Case: SOT-490 Plastic case Weight: approx. 2.5 mg Pinning: 1 = Collector, 2 = Base, 3 = Emitter

Parts Table

Part	Marking	Package		
S852TF	52	SOT-490		

Absolute Maximum Ratings

T_{amb} = 25 °C, unless otherwise specified

Parameter	Test condition	Symbol	Value	Unit
Collector-base voltage		V _{CBO}	12	V
Collector-emitter voltage		V _{CEO}	6	V
Emitter-base voltage		V _{EBO}	2	V
Collector current		Ι _C	8	mA
Total power dissipation	$T_{amb} \le 125 \ ^{\circ}C$	P _{tot}	30	mW
Junction temperature		Τ _j	150	°C
Storage temperature range		T _{stg}	- 65 to + 150	۵°

S852TF

Vishay Semiconductors



Maximum Thermal Resistance

Parameter	Test condition	Symbol	Value	Unit
Junction ambient	1)	R _{thJA}	450	K/W

 $^{1)}$ on glass fibre printed board (25 x 20 x 1.5) mm^3 plated with 35 μm Cu

Electrical DC Characteristics

 T_{amb} = 25 °C, unless otherwise specified

Parameter	Test condition	Symbol	Min	Тур.	Max	Unit
Collector-emitter cut-off current	$V_{CE} = 12 \text{ V}, V_{BE} = 0$	I _{CES}			100	μA
Collector-base cut-off current	$V_{CB} = 8 V, I_E = 0$	I _{CBO}			100	nA
Emitter-base cut-off current	$V_{EB} = 1 V, I_{C} = 0$	I _{EBO}			1	μA
Collector-emitter breakdown voltage	I _C = 1 mA, I _B = 0	V _{(BR)CEO}	6			V
Collector-emitter saturation voltage	$I_{\rm C} = 5$ mA, $I_{\rm B} = 0.5$ mA	V _{CEsat}		0.1	0.4	V
DC forward current transfer ratio	$V_{CE} = 5 \text{ V}, I_{C} = 30 \text{ mA}$	h _{FE}	40	90	150	




Vishay Semiconductors

Electrical AC Characteristics

 $T_{amb} = 25 \ ^{\circ}C$, unless otherwise specified

Parameter	Test condition	Symbol	Min	Тур.	Max	Unit
Transition frequency	$V_{CE} = 3 \text{ V}, \text{ I}_{C} = 1 \text{ mA},$ f = 500 MHz	f _T		4.7		GHz
	$V_{CE} = 2 V, I_C = 1.5 mA,$ f = 500 MHz	f _T		5.2		GHz
Collector-base capacitance	V _{CB} = 1 V, f = 1 MHz	C _{cb}		0.25		pF
Noise figure	$V_{CE} = 2 \text{ V}, I_C = 0.5 \text{ mA},$ $Z_S = Z_{Sopt}, f = 450 \text{ MHz}$	F _{opt}		1.1		dB
	$V_{CE} = 3 \text{ V}, I_C = 1 \text{ mA},$ $Z_S = Z_{Sopt}, f = 945 \text{ MHz}$	F _{opt}		1.7		dB
	V_{CE} = 2 V, I_C = 1.5 mA, Z_S = Z_{Sopt} , f = 945 MHz	F _{opt}		1.9		dB
Power gain	$V_{CE} = 2 \text{ V}, \text{ I}_{C} = 0.5 \text{ mA},$ f = 450 MHz	G _{pe} @ F _{opt}		11.5		dB
	$V_{CE} = 3 V, I_C = 1 mA,$ f = 945 MHz	G _{pe} @ F _{opt}		10.5		dB
	$V_{CE} = 2 V, I_C = 1.5 mA,$ f = 945 MHz	G _{pe} @ F _{opt}		12.5		dB
Transducer gain	$V_{CE} = 2 \text{ V}, \text{ I}_{C} = 1.5 \text{ mA},$ f = 945 MHz, Z _O = 50 Ω	S _{21e} ²		10		dB
Real part of input impedance	V _{CE} = 3 V, I _C = 1 mA, f = 945 MHz	Re _(h11e)		50		Ω
	V _{CE} = 2 V, I _C = 1.5 mA, f = 945 MHz	Re _(h11e)		50		Ω

Package Dimensions in mm



Vishay Semiconductors



Ozone Depleting Substances Policy Statement

It is the policy of Vishay Semiconductor GmbH to

- 1. Meet all present and future national and international statutory requirements.
- 2. Regularly and continuously improve the performance of our products, processes, distribution and operating systems with respect to their impact on the health and safety of our employees and the public, as well as their impact on the environment.

It is particular concern to control or eliminate releases of those substances into the atmosphere which are known as ozone depleting substances (ODSs).

The Montreal Protocol (1987) and its London Amendments (1990) intend to severely restrict the use of ODSs and forbid their use within the next ten years. Various national and international initiatives are pressing for an earlier ban on these substances.

Vishay Semiconductor GmbH has been able to use its policy of continuous improvements to eliminate the use of ODSs listed in the following documents.

- 1. Annex A, B and list of transitional substances of the Montreal Protocol and the London Amendments respectively
- 2. Class I and II ozone depleting substances in the Clean Air Act Amendments of 1990 by the Environmental Protection Agency (EPA) in the USA
- 3. Council Decision 88/540/EEC and 91/690/EEC Annex A, B and C (transitional substances) respectively.

Vishay Semiconductor GmbH can certify that our semiconductors are not manufactured with ozone depleting substances and do not contain such substances.

We reserve the right to make changes to improve technical design and may do so without further notice.

Parameters can vary in different applications. All operating parameters must be validated for each customer application by the customer. Should the buyer use Vishay Semiconductors products for any unintended or unauthorized application, the buyer shall indemnify Vishay Semiconductors against all claims, costs, damages, and expenses, arising out of, directly or indirectly, any claim of personal damage, injury or death associated with such unintended or unauthorized use.

Vishay Semiconductor GmbH, P.O.B. 3535, D-74025 Heilbronn, Germany



Vishay

Disclaimer

All product specifications and data are subject to change without notice.

Vishay Intertechnology, Inc., its affiliates, agents, and employees, and all persons acting on its or their behalf (collectively, "Vishay"), disclaim any and all liability for any errors, inaccuracies or incompleteness contained herein or in any other disclosure relating to any product.

Vishay disclaims any and all liability arising out of the use or application of any product described herein or of any information provided herein to the maximum extent permitted by law. The product specifications do not expand or otherwise modify Vishay's terms and conditions of purchase, including but not limited to the warranty expressed therein, which apply to these products.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted by this document or by any conduct of Vishay.

The products shown herein are not designed for use in medical, life-saving, or life-sustaining applications unless otherwise expressly indicated. Customers using or selling Vishay products not expressly indicated for use in such applications do so entirely at their own risk and agree to fully indemnify Vishay for any damages arising or resulting from such use or sale. Please contact authorized Vishay personnel to obtain written terms and conditions regarding products designed for such applications.

Product names and markings noted herein may be trademarks of their respective owners.