# SPECIFICATION FOR LCD MODULE

Model No. \_\_\_\_ **TM12232ABA** 

Prepared by: Date: Checked by: Date: Verified by: Date: Approved by: Date:

TIANMA MICROELECTRONICS CO., LTD

### **REVISION RECORD**

| Date | Ref. Page | Revision No. | Revision Items | Check & Approval |
|------|-----------|--------------|----------------|------------------|
|      |           |              |                |                  |
|      |           |              |                |                  |
|      |           |              |                |                  |
|      |           |              |                |                  |
|      |           |              |                |                  |
|      |           |              |                |                  |
|      |           |              |                |                  |
|      |           |              |                |                  |
|      |           |              |                |                  |
|      |           |              |                |                  |
|      |           |              |                |                  |
|      |           |              |                |                  |
|      |           |              |                |                  |
|      |           |              |                |                  |
|      |           |              |                |                  |
|      |           |              |                |                  |

### 1 General Specifications:

1.1 Display type: STN

1.2 Display color\*:

Display color: Blue-Black
Background: Yellow-Green

1.3 Polarizer mode: Reflective/Positive

1.4 Viewing Angle: 6:00

1.5 Driving Method: 1/32 Duty 1/6 Bias

1.6 Without Backlight

1.7 Controller: SED1520DOA

1.8 Data Transfer: 8 Bit Parallel

1.9 Operating Temperature: -0----+50 ℃

Storage Temperature: -20----+60 °C

1.10 Outline Dimensions: Refer to outline drawing on next page

1.11 Dot Matrix: 122X32 DOTS


1.12 Dot Size: 0.4X0.4(mm)

1.13 Dot Pitch: 0.44X0.44 (mm)


1.14 Weight: 60g

<sup>\*</sup> Color tone is slightly changed by temperature and driving voltage.


### 2 Outline Drawing



### 3 LCD Module Part Numbering System



# 4 Circuit Block Diagram



# **5 Absolute Maximum Ratings**

| Item                           | Symbol                           | Min.                                      | Max. | Unit       | Remark       |  |
|--------------------------------|----------------------------------|---|------|------------|--------------|--|
| Power Supply Voltage           | V <sub>DD</sub> -V <sub>SS</sub> | V <sub>DD</sub> -V <sub>SS</sub> -0.3 7.0 |      | V          |              |  |
| LCD Driving Voltage            | VLCD -0.3 13.0                   |   |      |            |              |  |
| Operating Temperature<br>Range | Тор                              | 0   | +50  | $^{\circ}$ | No           |  |
| Storage Temperature<br>Range   | Тѕт                              | -20                                       | +60  |            | Condensation |  |

# **6 Electrical Specifications and Instruction Code**

### 6.1 Electrical characteristics


| Iten                   | n    | Symbol   | Min.                 | Тур. | Max.                 | Unit |
|------------------------|------|--|----------------------|------|----------------------|------|
| Supply Voltage (Logic) |      | V <sub>DD</sub> -V <sub>SS</sub>                         | 4.5                  | 5.0  | 5.5                  | V    |
| Supply V<br>(LCD D     | _    | $ m V_{LCD}$   |                      |      |                      |      |
| Input                  | High | $V_{\text{IH}}$ $(V_{DD}=5.0)$                           | $0.7 { m V}_{ m DD}$ | -    | V <sub>DD</sub> +0.3 | V    |
| Signal<br>Voltage      | Low  | $V_{\text{\tiny IL}}$ $(V_{\text{DD}}=5.0)$              | -0.3                 | -    | 0.2 V <sub>DD</sub>  | V    |
| Supply c               |      | $I_{\text{DD}} \\ (V_{\text{DD}} - V_{\text{SS}} = 5.0)$ | -                    | -    | 6.0                  | mA   |
| Supply c               |      | $ m I_{ee}$  | -                    | -    | 1.0                  | mA   |

# 6.2 Interface Signals

| Pin No. | Symbol | Level | Description                               |
|---------|--------|-------|---|
| 1       | VSS    | 0V    | Ground                                    |
| 2       | VDD    | 5.0V  | Power supply voltage for logic and LCD(+) |
| 3       | VO     | -0.5V | Power supply voltage for LCD(-)           |
| 4       | A0     | H/L   | H: Display Data L: Instructions           |
| 5       | E1     | H/L   | IC1 Read/Write Enable Signal              |
| 6       | E2     | H/L   | IC2 Read/Write Enable Signal              |
| 7       | R/W    | H/L   | Read/Write Select Signal                  |
| 8       | D0     | H/L   | Data Bus Line                             |
| 9       | D1     | H/L   | Data Bus Line                             |
| 10      | D2     | H/L   | Data Bus Line                             |
| 11      | D3     | H/L   | Data Bus Line                             |
| 12      | D4     | H/L   | Data Bus Line                             |
| 13      | D5     | H/L   | Data Bus Line                             |
| 14      | D6     | H/L   | Data Bus Line                             |
| 15      | D7     | H/L   | Data Bus Line                             |
| 16      | /RST   | H/L   | Reset Signal                              |
| 17      | NC     | -     | No Connect                                |
| 18      | NC     | -     | No Connect                                |

# 6.3 Interface Timing Chart

# AC Characteristics(V<sub>DD</sub>=4.5V~5.5V,Ta=-20~+75 °C)



Ta=-20 to 75 deg. C

| Ci om al      | Crusals of   | Damamatan           | V <sub>DD</sub> =4.5 | to 5.5V | V <sub>DD</sub> =2.7 | to 5.5V | Linit     | Condition |
|---------------|--------------|---------------------|----------------------|---------|----------------------|---------|-----------|-----------|
| Signal Symbol | Parameter    | min                 | max                  | min     | max                  | Unit    | Condition |           |
| A0,CS         | $t_{AH8}$    | Address hold time   | 10                   | -       | 10                   | -       | ns        |           |
| A0,CS         | $t_{ m AW8}$ | Address setup time  | 0                    | -       | 0                    | -       | ns        |           |
| WD DD         | $t_{CYC8}$   | System cycle time   | See note.            | -       | See note.            | -       | ns        |           |
| WR,RD         | $t_{CC}$     | Strobe pulsewidth   | 120                  | -       | 150                  | -       | ns        | CL=100pF  |
|               | $t_{ m DS8}$ | Data setup time     | 120                  | -       | 120                  | -       | ns        |           |
| D0 to D7      | $t_{ m DH8}$ | Data hold time      | 5                    | -       | 5                    | -       | ns        |           |
| ם ולו טוט די  | $t_{ACC8}$   | RD access time      | -                    | 50      | -                    | 80      | ns        |           |
|               | $t_{ m OH8}$ | Output disable time | 10                   | 50      | 10                   | 55      | ns        |           |

Note


For memory control and system control commands:

$$t_{CYC8} = 2 t_C + t_{CC} + t_{CEA} + 75 > t_{ACV} + 245$$

for all other commands:

$$t_{CYC8} = 4 t_C + t_{CC} + 30$$

# 6800 family interface timing



Note

teros indicates the interval during which CS is LOW and E is HIGH

Ta=-20 to 75 deg. C

| G: 1       | 0 1 1              | D                   | V <sub>DD</sub> =4.5 | to 5.5V | V <sub>DD</sub> =2.7 | to 5.5V | TT '. | C 1'.'    |
|------------|--------------------|---------------------|----------------------|---------|----------------------|---------|-------|-----------|
| Signal     | Symbol             | Parameter           | min                  | Max     | min                  | max     | Unit  | Condition |
| 40.00      | $t_{\rm CYC6}$     | System cycle time   | See note.            | -       | See note.            | -       | ns    |           |
| A0,CS      | $t_{AW6}$          | Address setup time  | 0                    | -       | 10                   | -       | ns    |           |
| R/W        | $t_{AH6}$          | Address hold time   | 0                    | -       | 0                    | -       | ns    |           |
|            | $t_{ m DS6}$       | Data setup time     | 100                  | ı       | 120                  | ı       | ns    | CL=100pF  |
| D0 to D7   | $t_{ m DH6}$       | Data hold time      | 0                    | -       | 0                    | -       | ns    |           |
| Bo to B7   | $t_{\mathrm{OH6}}$ | Output disable time | 10                   | 50      | 10                   | 75      | ns    |           |
| $t_{ACC6}$ |                    | Access time         | -                    | 85      | -                    | 130     | ns    |           |
| Е          | $t_{\rm EW}$       | Enable pulsewidth   | 120                  | -       | 150                  | -       | ns    |           |

Note

For memory control and system control commands:

$$t_{CYC8} = 2 t_C + t_{CC} + t_{CEA} + 75 > t_{ACV} + 245$$

for all other commands:

$$t_{\rm CYC8} = 4 t_{\rm C} + t_{\rm EW} + 30$$

### 6.4 Instruction Code

| Command                    |    |    |    |      |           | Code       |                            |      |         |                                   |            | Command description   |
|----------------------------|----|----|----|------|-----------|------------|----------------------------|------|---------|-----------------------------------|------------|---|
|                            | RD | WR | A0 | D7   | D6        | D5         | D4                         | D3   | D2      | D1                                | D0         | -   |
| Display<br>On/Off          | 1  | 0  | 0  | 1    | 0         | 1          | 0                          | 1    | 1       | 1                                 | 0/1        | Switch the entire display on or off   |
| Display Start<br>Line      | 1  | 0  | 0  | 1    | 1         | 0          |                            | Disp | ay stai | rt line                           |            | Determine the line of RAM data to be displayed at the display top line(COM0)  |
| Page Address<br>Set        | 1  | 0  | 0  | 1    | 0         | 1          | 1                          | 1    | 0       |                                   | ige<br>-3) | Sets the page of the display<br>RAM in the page address<br>register   |
| Column(SEG)<br>Address Set | 1  | 0  | 0  | 0    |           | 0          | Column Address<br>(0 - 79) |      |         |                                   |            | Set the column address of the display RAM in the column address register  |
| Status Read                | 0  | 1  | 0  | Busy | ADC       | ON/<br>OFF | RESET                      | 0    | 0       | 0                                 | 0          | Read the status   |
| Write Display<br>Data      | 1  | 0  | 1  |      |           |            | Write                      | Data |         | Write Data on the data bus to RAM |            |   |
| Read Display<br>Data       | 0  | 1  | 1  |      | Read Data |            |                            |      |         |                                   |            | Read Data on the data bus to RAM  |
| ADC Select                 | 1  | 0  | 0  | 1    | 0         | 1          | 0                          | 0    | 0       | 0                                 | 0/1        | Used to reverse the correspondence between the display RAM's column addresses and segment driver output ports (0:forwaed 1:reverse) |
| Static Drive<br>On/Off     | 1  | 0  | 0  | 1    | 0         | 1          | 0                          | 0    | 1       | 0                                 | 0/1        | Select normal display<br>operation or static all-lit drive<br>display operation<br>(0::normal 1:static drive*)                      |
| Duty Select                | 1  | 0  | 0  | 1    | 0         | 1          | 0                          | 1    | 0       | 0                                 | 0/1        | Select the duty factor for<br>driving LCD cells<br>(0;1/16 1;1/32)  |
| Read Modify<br>Write       | 1  | 0  | 0  | 1    | 1         | 1          | 0                          | 0    | 0       | 0                                 | 0          | Increment the column address counter by one only when display data is written but not when it is read                               |
| End                        | 1  | 0  | 0  | 1    | 1         | 1          | 0                          | 1    | 1       | 1                                 | 0          | Cancel the read modify write mode   |
| Reset                      | 1  | 0  | 0  | 1    | 1         | 1          | 0                          | 0    | 0       | 1                                 | 0          | Reset the display   |

<sup>\*</sup> Power Save mode is entered by selecting static drive in the Display OFF status Notes

# 7 Optical Characteristics


# 7.1 Optical Characteristics

Ta=25 ℃


| Item          |             | Symbol                  | Con   | dition             | Min. | Тур. | Max. | Unit  |
|---------------|-------------|-------------------------|---|--------------------|------|------|------|-------|
| Viewing Angle |             | $\theta_{\!\mathbf{x}}$ | Cr≥2  | θ <sub>y</sub> =0° | -35  |      | 20   | Dog   |
|               |             | θу                      | Cr <u>~</u> 2                                 | θ <sub>x</sub> =0° | -30  |      | 30   | Deg   |
| Contrast 1    | Ratio       | Cr                      | $\theta_{x}=0^{\circ}$ $\theta_{y}=0^{\circ}$ |                    | 4.0  | -    | -    |       |
| Response      | Turn<br>on  | Ton                     | $\theta_{x}=0^{\circ}$ $\theta_{y}=0^{\circ}$ |                    | -    | -    | 250  | 444.0 |
| Time          | Turn<br>off | Toff                    | θy=   | =0°                | -    | -    | 250  | ms    |

### 7.2 Definition of Optical Characteristics

### 7.2.1 Definition of Viewing Angle




### 7.2.2 Definition of Contrast Ratio



Contrast Ratio =  $B2/B1 = \frac{\text{unselected state brightness}}{\text{selected state brightness}}$ 

Measuring Conditions:

1) Ambient Temperature: 25°C; 2) Frame frequency: 64.0Hz 7.2.3 Definition of Response time



Turn on time:  $t_{on} = t_d + t_r$ 

Turn off time:  $t_{off} = t_d + t_f$ 

Measuring Condition:

1) Operating Voltage: 5.5V

2) Frame frequency: 64.0Hz

# 8 Reliability

8.1 Content of Reliability Test

Ta=25°C

|     | I .               |  |                       |
|-----|-------------------|--|-----------------------|
| No. | Test Item         | Content of Test  | Test condition        |
| 1   | High Temperature  | Endurance test applying the high   | 60℃                   |
|     | Storage           | storage temperature for a long time  | 96H                   |
| 2   | Low Temperature   | Endurance test applying the low  | -20°C                 |
| 2   | Storage           | storage temperature for a long time  | 96H                   |
|     | High Temperature  | Endurance test applying the  |                       |
| 3   | Operation         | electric stress (voltage & current)  | 50°C                  |
| 3   |                   | and the thermal stress to the  | 96H                   |
|     |                   | element for a long time  |                       |
|     | Low Temperature   | Endurance test applying the  | $0^{\circ}\mathbb{C}$ |
| 4   | Operation         | electric stress under low  | 96H                   |
|     |                   | temperature for a long time  |                       |
|     | High Temperature  | Endurance test applying the high   | 40℃                   |
| 5   | /Humidity Storage | temperature and high humidity  | 90%RH                 |
|     |                   | storage for a long time  | 96H                   |
|     | Temperature       | Endurance test applying the low  | -20°C/60°C            |
|     | Cycle             | and high temperature cycle   |                       |
| 6   |                   | $-20^{\circ}\text{C} \longleftrightarrow 25^{\circ}\text{C} \longleftrightarrow 60^{\circ}\text{C} \longleftrightarrow 25^{\circ}\text{C}$ | 10 cycles             |
|     |                   | 30min 5min 30min 5min  ←   |                       |
|     |                   | 1 cycle  |                       |
|     | Vibration Test    | Endurance test applying the  | 10Hz~150Hz,           |
| 7   | (package state)   | vibration during transportation  | $50 \text{m/s}^2$ ,   |
|     |                   |  | 40min                 |
|     | Shock Test        | Endurance test applying the shock  | Half-sinewave,        |
| 8   | (package state)   | during transportation  | $100 \text{m/s}^2$ ,  |
|     |                   |  | 11ms                  |
|     | Atmospheric       | Endurance test applying the  | 40kPa                 |
| 9   | Pressure Test     | atmospheric pressure during  | 16H                   |
|     |                   | transportation by air  |                       |

# 8.2 Failure Judgment Criterion

| Criterion                   |          |  | Т        | est ]    | Iten     | n N | 0. |          |   | Failura Judament Criterian          |
|-----------------------------|----------|--|----------|----------|----------|-----|----|----------|---|-------------------------------------|
| Item                        | 1        | 2  | 3        | 4        | 5        | 6   | 7  | 8        | 9 | Failure Judgment Criterion          |
| Basic<br>Specification      | √        | <b>√</b>   | <b>√</b> | √        | √        | √   | √  | √        | √ | Out of the basic Specification      |
| Electrical specification    | <b>√</b> | <b>√</b>   | <b>√</b> | <b>√</b> | <b>√</b> |     |    |          |   | Out of the electrical specification |
| Mechanical<br>Specification |          |  |          |          |          |     | √  | <b>√</b> |   | Out of the mechanical specification |
| Optical<br>Characteristic   | <b>√</b> | <b>√</b>   | <b>√</b> | <b>√</b> | <b>√</b> | √   |    |          | √ | Out of the optical specification    |
| Note                        | Fo       | For test item refer to 8.1   |          |          |          |     |    |          |   |                                     |
| Remark                      |          | Basic specification = Optical specification + Mechanical specification |          |          |          |     |    |          |   |                                     |

### 9 QUALITY LEVEL

| Examination                      | At T <sub>op</sub> =25°C   | Inspection         |         |      |    |                              |  |  |
|----------------------------------|--|--------------------|---------|------|----|------------------------------|--|--|
| or Test                          | (unless otherwise stated)  | Min.               | Max.    | Unit | IL | AQL                          |  |  |
| External<br>Visual<br>Inspection | Under normal illumination and eyesight condition, the distance between eyes and LCD is 25cm. | See Appendix A     |         |      | II | Major<br>1.0<br>Minor<br>2.5 |  |  |
| Display<br>Defects               | Under normal illumination and eyesight condition, display on inspection.                     | See A <sub>1</sub> | ppendix | В    | II | Major<br>1.0<br>Minor<br>2.5 |  |  |

Note: Major defects: Open segment or common, Short, Serious damages, Leakage

Minor defects: Others

Sampling standard conforms to GB2828

### 10 Precautions for Use of LCD Modules

- 10.1 Handling Precautions
- 10.1.1 The display panel is made of glass. Do not subject it to a mechanical shock by dropping it from a high place, etc.
- 10.1.2 If the display panel is damaged and the liquid crystal substance inside it leaks out, be sure not to get any in your mouth, if the substance comes into contact with your skin or clothes, promptly wash it off using soap and water.
- 10.1.3 Do not apply excessive force to the display surface or the adjoining areas since this may cause the color tone to vary.
- 10.1.4 The polarizer covering the display surface of the LCD module is soft and easily scratched. Handle this polarizer carefully.
- 10.1.5 If the display surface is contaminated, breathe on the surface and gently wipe it with a soft dry cloth. If still not completely clear, moisten cloth with one of the following solvents:
  - Isopropyl alcohol
  - Ethyl alcohol

Solvents other than those mentioned above may damage the polarizer. Especially, do not use the following:

- Water
- Ketone
- Aromatic solvents
- 10.1.6 Do not attempt to disassemble the LCD Module.
- 10.1.7 If the logic circuit power is off, do not apply the input signals.
- 10.1.8 To prevent destruction of the elements by static electricity, be careful to maintain an optimum work environment.
  - a. Be sure to ground the body when handling the LCD Modules.
  - b. Tools required for assembly, such as soldering irons, must be properly ground.
  - c. To reduce the amount of static electricity generated, do not conduct assembly and other work under dry conditions.
  - d. The LCD Module is coated with a film to protect the display surface. Be care when peeling off this protective film since static electricity may be generated.

- 10.2 Storage precautions
- 10.2.1 When storing the LCD modules, avoid exposure to direct sunlight or to the light of fluorescent lamps.
- 10.2.2 The LCD modules should be stored under the storage temperature range. If the LCD modules will be stored for a long time, the recommend condition is:

Temperature:  $0^{\circ}\text{C} \sim 40^{\circ}\text{C}$ 

Relatively humidity: ≤80%

- 10.2.3 The LCD modules should be stored in the room without acid, alkali and harmful gas.
- 10.3 The LCD modules should be no falling and violent shocking during transportation, and also should avoid excessive press, water, damp and sunshine.

**Appendix A**Inspection items and criteria for appearance defects

| Items                  | Contents                   |                                 |                      | Criteria               |         |  |  |
|------------------------|----------------------------|---------------------------------|----------------------|------------------------|---------|--|--|
| Leakage                |                            | Not permitted                   |                      |                        |         |  |  |
| Rainbow                |                            | According to the limit specimen |                      |                        |         |  |  |
|                        | Wrong polarizer attachment | Not permitted                   | I                    |                        |         |  |  |
| Polarizer              | Bubble between             | Not counted                     |                      | Max. 3 defects al      | lowed   |  |  |
|                        | polarizer and glass        | ф<0.3mm                         |                      | 0.3mm≤¢≤0.5r           | nm      |  |  |
|                        | Scratches of polarizer     | According to the limit specimen |                      |                        |         |  |  |
| Black spot             |                            | Not counted                     | Max. 3 spots allowed |                        |         |  |  |
| (in viewing area)      |                            | X<0.20mm                        | 0.201                | mm≤X≤0.5mm             | Max. 3  |  |  |
| died)                  | 0                          | X=(a+b)/2                       | spots (lines)        |                        |         |  |  |
| Black line (in viewing | •                          | Not counted                     | Max                  | . 3 lines allowed      | allowed |  |  |
| area)                  | 0                          | a<0.02mm                        | 0.021                | mm≤a≤0.05mm<br>b≤2.0mm |         |  |  |
| Progressive cracks     |                            | Not permitted                   |                      |                        |         |  |  |

Appendix B
Inspection items and criteria for display defects

| Items  |       | Contents         | Criteria                        |                     |                           |
|--|-------|------------------|---------------------------------|---------------------|---------------------------|
| Open segment or open common                    |       |                  | Not permitted                   |                     |                           |
| Short  |       |                  | Not permitted                   |                     |                           |
| Wrong viewing angle                            |       |                  | Not permitted                   |                     |                           |
| Contrast radio uneven                          |       |                  | According to the limit specimen |                     |                           |
| Crosstalk                                      |       |                  | According to the limit specimen |                     |                           |
|  | -     | <del> </del>  -a | Not counted                     | Max.3 dots allowed  |                           |
| Pin holes<br>and cracks<br>in segment<br>(DOT) | 7 0 0 |                  | X<0.1mm                         | 0.1mm≤X≤0.2mm       |                           |
|  |       | X=(a+b)/2        |                                 | Max.3<br>dots       |                           |
|  | -  -D | Not counted      | Max.2 dots allowed              | allowed             |                           |
|  | 1     |                  | A<0.1mm                         |                     | 0.1mm≤A≤0.2mm<br>D<0.25mm |
| Black spot (in viewing area)                   |       |                  | Not counted                     | Max.3 spots allowed |                           |
|  |       |                  | X<0.1mm                         | 0.1mm≤X≤0.2mm       |                           |
| urcu)  |       | X=(a+b)/2        |                                 | Max.3 spots         |                           |
| Black line<br>(in viewing<br>area)             |       |                  | Not counted                     | Max.3 lines allowed | (lines)<br>allowed        |
|  | b b   | a<0.02mm         | 0.02mm≤a≤0.05mm<br>b≤0.5mm      |                     |                           |

Appendix B
Inspection items and criteria for display defects (continued)

| Items                             | Content     | Critera   |                        |                             |  |  |
|-----------------------------------|-------------|---|------------------------|-----------------------------|--|--|
| Transfor-<br>mation<br>of segment | and have to | Not counted   | Max. 2 defects allowed |                             |  |  |
|                                   |             | x<0.1mm   | 0.1mm≤x≤0.2mm          |                             |  |  |
|                                   |             | x=(a+b)/2   |                        | May 2                       |  |  |
|                                   | D-+1+1+-α   | Not counted   | Max. 1 defects allowed | Max.3<br>defects<br>allowed |  |  |
|                                   |             | a<0.1mm   | 0.1mm≤a≤0.2mm<br>D>0   |                             |  |  |
|                                   |             | Max.2 defects allowed 0.8W≤a≤1.2W  a=measured value of width W=nominal value of width |                        |                             |  |  |