

DESCRIPTION

The SPE0589 is an ESD transient voltage suppression component which provides a very high level of protection for sensitive electronic components that may be subjected to electrostatic discharge (ESD).

It is particularly well-suited for cellular phones, portable device, digital cameras, power supplies and many other portable applications because of its small package and low weight. The SPE0589 is Uni-directional, Safely dissipate ESD strikes of Level 4, IEC61000-4-2, exceeding the maximum requirement. Using the MILSTD-883 (Method 3015) specification for Human Body Model (HBM) ESD, the device provides protection for contact discharges to greater than +/-10KV. The SPE0589 is available in a WBFBP-02C package with peak reverse working voltage of 5 voltages.

APPLICATIONS

- Cellular Handsets and Accessories
- ◆ Cordless Phone
- ◆ PDA
- Notebooks and Handhelds
- ◆ Portable Instrumentation
- ◆ Digital Cameras
- ♦ MP3 Player

FEATURES

◆ Transient protection for data lines to


IEC 61000-4-2 (ESD) ±15kV (air) ±8kV (contact)

IEC 61000-4-4 (EFT) 40A (5/50ns)

- ◆ Protects single I/O lines
- ♦ Working voltage: 5V
- ◆ Low leakage current
- ◆ Low operating and clamping voltages
- ♦ Small Body Outline: 1.0 x 0.6 x 0.5mm

PIN CONFIGURATION (FBP-02C)





PART MARKING



M= Month Code x=Specific Device Code

ORDERING INFORMATION

Part Number	Package	Part Marking
SPE0589BP02RGB	FBP-02C	Mx

M=Month Code (A~Z)

★ SPE0589BP02RGB: Tape Reel; Pb – Free; Halogen – Free

ABSOULTE MAXIMUM RATINGS

(Ta=25°C Unless otherwise noted)

Parameter	Symbol	Typical	Unit
Peak Pulse Power ($tp = 8/20 \mu s$)	Ppk	180	W
Maximum Peak Pulse Current (tp = 8/20 μs)	Ipp	7	A
ESD per IEC 61000 – 4 – 2 (Air)	Vpp	±15	KV
ESD per IEC 61000 – 4 – 2 (Contact)	Vpp	±10	KV
Operating Junction Temperature	Тл	- 55 ∼ 125	$^{\circ}\!\mathbb{C}$
Storage Temperature Range	Tstg	- 55 ∼ 150	$^{\circ}\! \mathbb{C}$
Lead Soldering Temperature	TL	260 (10sec)	$^{\circ}\! \mathbb{C}$

ELECTRICAL CHARACTERISTICS

(Ta=25°C Unless otherwise noted)

Parameter	Symbol	Conditions	Min.	Тур	Max.	Unit
Reverse Stand – Off Voltage	Vrwm				5	V
Reverse Breakdown Voltage	VBR	It = 1mA	6			V
Reverse Leakage Current	Ir	$V_{RWM} = 5V$, $T=25^{\circ}C$			1	μΑ
Clamping Voltage	Vc	$Ipp = 1A$, $tp = 8/20 \mu s$			8	V
Junction Capacitance	Cj	Between I/O Pin and GND V _R = 0V, f = 1MHz		0.5	0.9	pF

TYPICAL CHARACTERISTICS




Figure 1. 8 X 20 μs Pulse Waveform




Figure 2. ESD Clamping Voltage Screenshot Positive 8 kV Contact per IEC61000-4-2






Figure 3. ESD Clamping Voltage Screenshot Negative 8 kV Contact per IEC61000-4-2




FBP-02C PACKAGE OUTLINE





Top View

Bottom View



Side View

Symbol	Dimensions In Millimeters		Dimensions In Inches		
	Min.	Max.	Min.	Max.	
A	0. 450	0. 550	0. 018	0.022	
A1	0.010	0.070	0.000	0.003	
D	0. 950	1. 050	0. 037	0.041	
Е	0. 550	0.650	0. 022	0.026	
D1	0. 450REF.		0. 018REF.		
E1	0. 400REF.		0.016REF.		
Ъ	0. 275	0. 325	0. 011	0.013	
е	0. 675	0. 725	0.027	0.029	
L	0. 275	0. 325	0. 011	0.013	
L1	0. 010REF.		0. 000REF.		

Information provided is alleged to be exact and consistent. SYNC Power Corporation presumes no responsibility for the penalties of use of such information or for any violation of patents or other rights of third parties which may result from its use. No license is granted by allegation or otherwise under any patent or patent rights of SYNC Power Corporation. Conditions mentioned in this publication are subject to change without notice. This publication surpasses and replaces all information previously supplied. SYNC Power Corporation products are not authorized for use as critical components in life support devices or systems without express written approval of SYNC Power Corporation.

©The SYNC Power logo is a registered trademark of SYNC Power Corporation
©2004 SYNC Power Corporation – Printed in Taiwan – All Rights Reserved
SYNC Power Corporation
7F-2, No.3-1, Park Street
NanKang District (NKSP), Taipei, Taiwan, 115, R.O.C
Phone: 886-2-2655-8178

Fax: 886-2-2655-8468 ©http://www.syncpower.com